



82546EB to 82546GB Migration

Application Note (AP-484)



Information in this document is provided in connection with Intel products. No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted by this document. Except as provided in Intel's Terms and Conditions of Sale for such products, Intel assumes no liability whatsoever, and Intel disclaims any express or implied warranty, relating to sale and/or use of Intel products including liability or warranties relating to fitness for a particular purpose, merchantability, or infringement of any patent, copyright or other intellectual property right. Intel products are not intended for use in medical, life saving, or life sustaining applications.

Intel may make changes to specifications and product descriptions at any time, without notice.

Designers must not rely on the absence or characteristics of any features or instructions marked "reserved" or "undefined." Intel reserves these for future definition and shall have no responsibility whatsoever for conflicts or incompatibilities arising from future changes to them.

The 82546EB and 82546GB Gigabit Ethernet Controllers may contain design defects or errors known as errata which may cause the product to deviate from published specifications. Current characterized errata are available on request.

Contact your local Intel sales office or your distributor to obtain the latest specifications and before placing your product order.

Copies of documents which have an ordering number and are referenced in this document, or other Intel literature may be obtained by calling 1-800-548-4725 or by visiting Intel's Web site at <http://www.intel.com>.

Copyright © 2005, Intel Corporation. All rights reserved.

* Other product and corporate names may be trademarks of other companies and are used only for explanation and to the owners' benefit without intent to infringe.



Revision History

Revision	Revision Date	Description
1.0	June 2005	Initial release



Note: This page intentionally left blank.

1.0 Introduction and Scope

The document explains the differences between an Intel® 82546EB Gigabit Ethernet Controller-based design and an Intel® 82546GB Ethernet Controller-based design. The primary differences are:

- Device IDs
- New 82546GB Features
- Resolved 82546EB Errata

2.0 Reference Documents

- 8254x Family of Gigabit Ethernet Controllers Software Developer's Manual, Intel Corporation.
- 82546GB Dual Port Gigabit Ethernet Controller Datasheet, Intel Corporation.
- 82546EB Dual Port Gigabit Ethernet Controller Datasheet, Intel Corporation.
- 82545EM, 82545GM, 82546EB, and 82546GB Gigabit Ethernet Controllers Design Guide.
- PCI Local Bus Specification, Revision 2.3, PCI Special Interest Group.
- PCI-X Specification, Revision 1.0a, PCI Special Interest Group.
- PCI Bus Power Management Interface Specification, Rev. 1.1, PCI Special Interest Group.

3.0 Pin Compatibility

The 82546GB is a pin compatible drop-in replacement for the 82546EB. Refer to the *82546GB Dual Port Gigabit Ethernet Controller Datasheet* for package and pinout information.

4.0 Device IDs

Table 1 lists the device IDs for both the 82546EB and 82546GB Gigabit Ethernet Controllers.

Table 1. Component Identification

Stepping	Vendor ID	Device ID	Description
82546GB	8086h	1079h	Copper; Dual Port
82546GB	8086h	107Ah	Fiber; Dual Port
82546GB	8086h	107Bh	SerDes; Dual Port
82546EB	8086h	1010h	Copper; Dual Port
82546EB	8086h	1012h	Fiber; Dual Port

5.0 New 82546GB Features

- Device ID - Created a new default device ID to identify the 82546GB
- PCI Configuration Map:
 - PCI: 00-3Ch
 - PCI Power Management: DC-E0h
 - PCI-X: E4-E8h
 - Message Signaled Interrupt: F0-FCh
- EEPROM Circuit Control Word 21h setting for PCI-X Driver Strength: FF63h
- Improved PCI-X V/I curves - V/I curves are centered relative to specification minima and maxima
- PICMG 3.1 compliant SerDes interface - Stronger drive strength and lower pre-emphasis to the SerDes transmitter
- VLAN management filters - Able to filter up to four different VLAN IDs for management
- IPMI I²C addressing capability - Allows IPMI implementations to follow I²C formats instead of SMBus formats
- IPMI MAC read capability - Enables the BMC to read the assigned MAC address of the 82546GB
- PCI 2.3 compliance - Includes PCI 2.3 compatible interrupt bits
- Full 2/3-wire downshift capabilities:
 - Enables downshift to 10/100 link when pair three or four is damaged
 - Enabled by default instead of requiring driver initialization
- Disabled gigabit half-duplex advertisement in copper PHY - Saves the software device driver from a re-negotiation event

6.0 Resolved 82546EB Errata

The following 82546EB Errata were resolved in the 82546GB Gigabit Ethernet Controller:

- Erratum #08 – 1.5V Regulator Control Circuit Start Up:
 - A generic BCP69 can be used without a CTRL15 pull-down resistor
- Erratum #12 – Bus Initialization With Some Chipsets:
 - A 0 ns hold time relative to RST# is now acceptable for a PCI-X configuration
- Erratum #14 – ASF Lockup Upon Resetting MAC:
 - A lockup condition was removed by changing the manageability logic
- Erratum #15 – REQ# Pin Requires Pull-Up Resistor in PCI-X Mode:
 - REQ# logic was changed to always drive thus eliminating the need for a pull-up resistor
- Erratum #16 – INTA# / INTB# Configuration on 82546EB Controller:
 - Interrupts are now correctly routed to the correct INTx# pins when the ports are disabled
- Erratum #17 – MWI Trans. May Terminate on Non-Cacheline Boundary:
 - PCI logic was changed to use a memory write transaction on non-cacheline writes
- Erratum #19 – PCI-X Maximum Read Burst When Programmed:
 - PCI-X logic was changed to use the smaller of the two values
- Erratum #20 – Master Aborts With Some Chipsets During Driver Reset:
 - An additional register with a software reset bit was added to the high DWORD to avoid a master abort
- Erratum #24 – Address Error Crossing 64KB Boundary:
 - An error condition was corrected to allow for 64 KB boundary crossings
- Erratum #25 – Intermittent Issues with TCO Receive Packets in IPMI Mode:
 - Corrected the TCO Receive FIFO logic to avoid an indeterminate state
- Erratum #29 – ASF RMCP ACK Packets May be Incorrectly ACK'ed:
 - A logic issue in the ASF logic was corrected to avoid sending an ACK to a received ACK
- Erratum #31 - Memory Access Must be Enabled in Order to Read Device Registers in I/O Mode:
 - Device registers can now be accessed in I/O mode with only the I/O Access Enable bit set

Note: Refer to the *82546GB Gigabit Ethernet Controller Specification Update* for additional Errata information.

Note: This page intentionally left blank.