

Intel® System Studio 2020 Update 3 Release Notes

19 October 2020

Contents

1	Introduction	2
2	System Requirements and What's New	2
3	Product Contents and Cross Reference	3
3.1	Intel® Software Manager	4
4	Technical Support and Documentation	5
4.1	Technical Support	5
4.2	Documentation Locations	5
5	Installation Notes and Log Files	6
6	Known Issues and Limitations	7
6.1	General Known Issues and Limitations	7
6.1.1	Intel® System Studio 2020 Windows* target cannot co-exist with older versions... ..	7
6.1.2	Intel® System Studio installation on Windows* host may cause a system restart ..	7
6.1.3	Upgrading Intel® System Studio may result in incorrect component selection	7
6.1.4	Intel® System Studio installer might not promote uninstall option for an installed product	7
6.1.5	Upgrading Intel® System Studio for Windows* may prevent OpenCL™ tools uninstall	7
6.1.6	Some hyperlinks in HTML documents may not work with Internet Explorer*	8
6.1.7	Host Operating System Requirements	8
6.1.8	End User License Agreement	8
6.2	Issues and Limitations by Component	8
7	Attributions	14
8	Notices and Disclaimers	15

1 Introduction

This document provides an overview of the **Intel® System Studio 2020 Update 3** product and provides pointers to where you can find new features and changes, the release history, installation instructions additional product information and references to articles and white papers.

Intel® System Studio has separate download packages for Linux* and Windows* hosts.

The target audience is the performance-oriented C/C++ embedded/mobile/wearable/IoT developer who is developing on Linux*, Windows*, and/or macOS* host environments for Yocto Project* embedded Linux*, Wind River* Linux*, and/or Android* targets.

For full product information, please refer to Intel® System Studio product webpage <https://software.intel.com/intel-system-studio>.

For licensing information, please refer to the Intel End User Licensing Agreement (EULA) available at <https://software.intel.com/articles/end-user-license-agreement>.

2 System Requirements and What's New

System requirements and what's new in Intel® System Studio 2020 Update 3 are available online: <https://software.intel.com/en-us/articles/intel-system-studio-release-notes-whats-new>

3 Product Contents and Cross Reference

The following table outlines which versions of the Intel® Software Development Tools are present in Intel® System Studio 2020 Update 3.

Component	Version
Docker* based build system	2020.3
Eclipse* IDE	2.2.12 (2020-05)
Yocto Project* Compatible Application Development Plugins	2.2.12
GNU* GDB and source	8.3.4
Intel® C/C++ Compiler	19.1.3
Intel® Data Analytics Acceleration Library (Intel® DAAL)	2020.0.3
Intel® Integrated Performance Primitives (Intel® IPP)	2020.0.3
Intel® Math Kernel Library (Intel® MKL)	2020.0.4
Intel® Threading Building Blocks (Intel® TBB)	2020.0.3
OpenCL™ Tools	2020
IoT Connection Tools (UPM / MRAA / Cloud Connectors)	2020
Sample Applications	N/A
Intel® Advisor 2020	2020.3.0
Intel® Inspector 2020	2020.3.0
Intel® SoC Watch for Android* targets	2020.3.2
Intel® SoC Watch for Linux* targets	2020.3.2
Intel® SoC Watch for Windows* targets	2020.3.2
Intel® VTune™ Profiler 2020	2020.3.0
Intel® VTune™ Platform Profiler	2020.3.0
Intel® Debug Extensions for WinDbg*	2020.3
Intel® System Debugger (System Debug & System Trace)	2020.3

Release notes for individual components are linked to from the main release notes page:
<https://software.intel.com/en-us/articles/intel-system-studio-release-notes-whats-new>

This document uses this label to represent the directory path where the product is installed:
<INSTALL_DIR>

Where the <INSTALL_DIR> is by default:

Windows* Host:

Windows Target: C:\Program Files (x86)\IntelSWTools\system_studio_2020

Linux Target: C:\IntelSWTools\system_studio_2020

Linux* Host:

sudo/root install: /opt/intel/system_studio_2020

macOS*:

/opt/intel/system_studio_2020

3.1 Intel® Software Manager

The Intel® Software Manager, automatically installed with the Intel® System Studio product on Windows* host systems, is a graphical tool that provides a simplified delivery mechanism for product updates, current license status, and news on all installed Intel Software Development tools.

It can also be manually started as well from these locations:

- Windows* 10: Launch the *Intel® Software Manager* application for the start screen.

The software manager from this release replaces any previous installed software manager and manages all installed Intel® Software Development Tools licenses on the system.

When you install Intel® System Studio, we collect information that helps us understand your installation status and environment. Information collected is anonymous and is not shared outside of Intel. See <https://software.intel.com/en-us/articles/data-collection> for more information on what is collected and how to opt-out.

You can also volunteer to provide Intel anonymous usage information about these products to help guide future product design. This option, the Intel® Software Improvement Program, is not enabled by default – you can opt-in during installation or at a later time, and may opt-out at any time. For more information please see <http://intel.ly/SoftwareImprovementProgram>

4 Technical Support and Documentation

4.1 Technical Support

Registration entitles you to free technical support, free product updates, and free product upgrades for the duration of the support term.

Technical support is provided through [Intel Online Service Center](#). You will receive private support for questions on the product. Select the “Intel® System Studio” product when submitting questions on the product. See [this article](#) for step-by-step guidance on submitting a support request.

Additionally, you may submit questions and browse issues in the [Intel® System Studio User Forum](#).

For additional information about how to find Technical Support, please visit:

<https://software.intel.com/intel-system-studio-support>.

Note: If your distributor provides technical support for this product, please contact them for support rather than Intel.

4.2 Documentation Locations

The main page for additional information, to download the package, the latest technical documentation, and information about finding technical support can be found here:

<https://software.intel.com/en-us/system-studio/documentation>

5 Installation Notes and Log Files

Please refer to the [System Requirements](#) to check the prerequisites for installing the Intel® System Studio 2020 Update 3 product.

If you run into issues installing the tools, you can refer to the README provided with the installer for more information.

Additionally, if you would like to see the install logs (helpful for reporting issues) you can find them here:

Linux* Host / Linux Target:

The Intel System Studio installer writes log files to /tmp, one for the user and one for root (when the installer is run with sudo). These log file names start with intel.pset, end with a timestamp and have the extension .log.

Windows* Host:

The Intel System Studio installer writes log files to %TEMP%\Intel\. The primary installer log file names begin with intel.pset and have the extension .log, and other Intel System Studio component installation log files have the extension .log. Additionally, if Intel System Studio components are integrated into Visual Studio*, VSIXInstaller_*.log and dd_setup_*.log files are written to the %TEMP% directory.

macOS* Host / Linux* Target:

The Intel System Studio installer writes log files to the system temp directory (echo \$TMPDIR), one for the user and one for root (when the installer is run with sudo). These log file names start with intel.pset, end with a timestamp and have the extension .log.

6 Known Issues and Limitations

For the complete list of known issues of individual Intel® System Studio 2020 Update 3 components, please refer to the individual component release notes:

<https://software.intel.com/en-us/articles/intel-system-studio-release-notes-whats-new>

6.1 General Known Issues and Limitations

6.1.1 Intel® System Studio 2020 Windows* target cannot co-exist with older versions

Intel® System Studio 2020 Windows* target contains new installation technology which is not fully compatible with Intel System Studio 2019 or Intel® Parallel Studio XE 2019, and earlier. To install Intel System Studio 2020 Update 3 on a system where Intel System Studio 2019 or Intel Parallel Studio XE 2019 or earlier has been installed, first uninstall the older version.

6.1.2 Intel® System Studio installation on Windows* host may cause a system restart

While installing Intel® System Studio 2020 Update 3 Ultimate Edition on a Windows* host, the system may try to reboot. If the reboot is cancelled, the Intel System Studio installer may display error messages. To work around this issue, re-run the Intel System Studio installation.

6.1.3 Upgrading Intel® System Studio may result in incorrect component selection

Running the Intel® System Studio 2020 installer from the installed product folder and selecting "Upgrade the installation" may result in the incorrect component selection on tool selection dialog. Components that are not selected might be deleted. To work around this issue, select required components on tool selection dialog before upgrade process or install missing components after upgrade using the installer's "Modify" option.

6.1.4 Intel® System Studio installer might not promote uninstall option for an installed product

Sometimes, the intel® System Studio installer process may be interrupted and closed forcefully by the system after the installation is complete. This may result in the situation where the installer from the installed product folder will not show 'Upgrade', 'Modify', or 'Uninstall' option. To work around this issue, open (create if not exists) file <System Studio installation folder>/pset/yum.prefs, add the string "IS_CACHED=yes", save the file, and restart the installer.

6.1.5 Upgrading Intel® System Studio for Windows* may prevent OpenCL™ tools uninstall

Upgrading Intel® System Studio 2020 for Windows* target to Update 3 may result in installer database corruption preventing uninstall of OpenCL™ Tools during modify or uninstall, with some folders and Visual Studio extensions remaining on the system. To completely uninstall this component, run the following command in a Windows command prompt:

```
MsiExec.exe /x {78AD81C2-ED7B-49F5-B547-66E6BC2377AF}
```

```
MsiExec.exe /x {9DFC7D22-9F4C-45C9-A509-AFD2FBFBC3EC}
```

6.1.6 Some hyperlinks in HTML documents may not work with Internet Explorer*

Try using another browser, such as Google Chrome* or Mozilla Firefox*, or right-click the link, select Copy shortcut, and paste the link into a new Internet Explorer* window.

6.1.7 Host Operating System Requirements

Intel® VTune™ Profiler, Intel® Advisor, and Intel® Inspector graphical user interfaces may require newer versions of host operating systems. See the individual components' release notes for details.

6.1.8 End User License Agreement

The top-level third-party-programs.txt file in the Intel® System Studio Composer and Professional Edition packages incorrectly states that Intel® System Debugger is distributed under the “End User License Agreement for the Intel(R) Software Development Products (Version October 2018)” license. The Intel System Debugger is distributed under the “Intel End User License Agreement for Developer Tools (Version September 2019)” license.

NOTE: The Intel System Debugger tool is distributed as part of the Ultimate Edition package of Intel System Studio. The license statement regarding Intel System Debugger in the top-level third-party-programs.txt file, in the Ultimate Edition package, is correct.

6.2 Issues and Limitations by Component

The Intel® System Studio cross-compile setup panel does not work (ISS-3711). It will be fixed in the next Intel System Studio update.

If you are trying to use Eclipse to cross-compile Yocto Project* applications you can use the Intel System Studio Yocto Project plug-in. Documentation can be found at <https://software.intel.com/en-us/developing-yocto-project-apps-with-intel-system-studio>

Alternatively, for developing Yocto Project applications with Eclipse, you may be able to use the Yocto Project Eclipse plug-in. For more information, see <https://www.yoctoproject.org/docs/2.6/sdk-manual/sdk-manual.html#sdk-eclipse-project>

For building Yocto Project applications at the command line, see the “App Development: When the Yocto SDK is Not Built with icc Environment Scripts” section of <https://software.intel.com/en-us/intel-system-studio-cplusplus-compiler-user-and-reference-guide-building-yocto-project-images-and-applications-from-the-command-line>

For more general-purpose command line cross-compile instructions with ICC, see the --sysroot and -gnu-prefix options described in <https://software.intel.com/en-us/articles/improved-sysroot-support-in-intel-c-compiler-for-cross-compile>

Component	Description	Implication	Workaround
Cmake build system (ISS-3058)	Binary is not configured for cmake native projects.	Users see “Binary Not Found” errors when running a cmake-based sample.	Manually create a local run configuration and set the field “C/C++ Application” to a binary in the project.
Docker* based build system	Docker is not provided with Intel® System Studio installation.	Container based project will fail on these systems without additional setup.	Users must follow the Installing Docker* for Intel System Studio guide to build their projects: <ul style="list-style-type: none"> • https://software.intel.com/en-us/intel-system-studio-docker-install-why
Docker* based build system	Installing and using the Intel System Studio Eclipse build system on a virtual machine is only supported by and has only been tested for Ubuntu* Desktop 16.04 and 18.04 Linux* guest virtual machines. Other guest operating systems (Windows* and macOS*) have not been tested and are not supported.	Some Intel System Studio features (e.g., Docker* and Intel VTune Amplifier) require access to low-level CPU features that are not supported by all virtual machine managers or hypervisors or are not enabled by default.	Install Intel System Studio onto a "real" Windows* or macOS* system, not a guest VM. If you must use a VM we recommend using an Ubuntu 16.04 or 18.04 guest VM with "nested virtualization" enabled and with at least 4GB of RAM dedicated to the VM
Docker* based build system	Removal or manual modification of Docker images and containers created by Intel System Studio (especially while Intel System Studio is running) may result in errors.	Existing projects may stop working. New projects in an existing workspace will not work.	To recover after removing a container or image, restart Intel System Studio. When both image and container have been removed, Intel System Studio prompts the user to redownload the image. The container is recreated after the image has downloaded.
Docker* based build system	Each release of Intel System Studio comes with a standard Docker* image that has been updated since the previous release. When a new release of Intel System Studio is installed, the updated image is not automatically installed.	The user can either continue using existing Intel System Studio Docker* image (e.g., if the image has been customized), or install the new Docker image.	To install a new Docker* image, see Installing a New Intel System Studio Docker Image at https://software.intel.com/en-us/intel-system-studio-docker-update-image
Docker* based build system (ISS-3552)	The first time a project is built in a workspace using an Ubuntu 18.04 container, the Eclipse* C++ indexer cannot correctly identify the C++ standard library paths and reports indexing errors, even though the project can be built without errors as can be verified in the console.	This problem is specific to the first project in the workspace and won't happen for subsequent projects.	To resolve this issue, close Eclipse and reopen it.

Eclipse* based IDE	On Red Hat* and CentOS* Hosts the welcome screen in the Intel System Studio IDE may be empty, non-responsive or display an error message.	Users will be unable to read welcome screen content.	User must install "epel-release" and "webkitgtk" packages using the following commands at a bash shell (in a terminal window): \$ sudo yum install epel-release \$ sudo yum install webkitgtk
Eclipse* based IDE	The Sensor View is not supported in the projects imported from Arduino* Create.	Users will not see the sensor view for projects imported from Arduino* Create.	Add sensors library code manually. Create a new C/C++ Docker*-based project, and use it to access the Sensor View.
Eclipse* based IDE (ISS-1877)	Creating a new project with the same name as an existing project folder results in an "Invalid thread access" error message.	The new project may fail to be created or files may be added and/or replaced in the existing project folder.	Do not use the name of an existing folder in the workspace. Open the workspace folder using OS file explorer to see all folders, as some folders may not appear in the Eclipse file / project explorer.
Eclipse* based IDE (ISS-1946)	Connecting to an application development target from Intel System Studio IDE freezes at 25% progress after initial connection succeeded.	The project cannot be launched on the target.	To work around this issue, reboot the target.
Eclipse* based IDE (Linux* host) (ISS-1953)	By default, Intel System Studio displays web content using the Eclipse internal browser.	The internal browser uses global proxy settings configured via Network Manager, not the Eclipse proxy configuration. When global proxy settings are not configured to allow internet access, external web content cannot be displayed in the Eclipse internal browser.	If it is not possible to configure global proxy settings (e.g., Network Manager is not available), web content can be displayed in an external browser. Open Preferences->General->Web Browser, then select "Use external web browser." Ensure the selected browser has internet access. When web content links are selected in Intel System Studio, the content will be displayed in the selected browser.
Eclipse* based IDE (ISS-2060)	Intel System Studio has Intel Advisor samples. These samples require advisor variable script to be sourced.	Advisor samples will not work without sourcing the advixe-var.sh script.	Before launching Intel System Studio, open a terminal and follow these commands: 1. source <install_dir>/advisor_2020/advixe-vars.sh 2. launch eclipse from same terminal using ./iss_ide_eclipse-launcher.sh

Eclipse* based IDE (ISS-2217)	Connecting to remote target fails because secure storage fails silently on some Linux systems.	When connecting to a remote target, the user is repeatedly prompted for login credentials, even after providing correct user name and password.	In Intel System Studio, select Settings > General > Security > Secure Storage, uncheck "Linux integration" master password provider and restart Intel System Studio.
Eclipse* based IDE (ISSDEV-2455)	"Save credentials" checkbox in the Connection Login dialog does not work on some Linux systems.	After entering username and password and checking the "Save credentials" checkbox, credentials are not actually saved.	In Intel System Studio, select Settings > General > Security > Secure Storage, uncheck "Linux integration" master password provider and restart Intel System Studio.
Eclipse* based IDE (ISS-2405)	"Intel Application Development" > "Project to cross compile C/C++ for Linux and Android targets" project setup dialog is confusing.	This workflow requires that pre-requisites listed in the Intel® System Studio 2020 Update 3 System Requirements document have been installed. These pre-requisites are not listed in Intel C++ Compiler 19.1 documentation referenced by the workflow.	gcc and binutils must be installed to use Intel C++ Compiler 19.1 (refer to system requirements at https://software.intel.com/en-us/articles/intel-system-studio-release-notes-whats-new). On Ubuntu, these can be installed via the build-essential package (`sudo apt-get install build-essential`). Other Linux distributions have similar packages. On Windows, a cross-compile environment such as Cygwin* or mingw* is required.
Eclipse* based IDE (ISS-2405)	By default, new C/C++ Remote Application Run configurations use the "Legacy Remote Create Process Launcher."	In some cases, this launcher is unable to connect to correctly configured targets. The "Remote Launching via TCF/TE Launcher" is compatible with connections created using the Connection toolbar in Intel System Studio and may be used instead of the "Legacy Remote Create Process Launcher".	To switch to the "Remote Launching via TCF/TE Launcher", click the "Select other" link at the bottom of the "Run Configurations" dialog. Click "Change Workspace Settings" in the "Select Preferred Launcher" dialog. Scroll down to "C/C++ Remote Application" and select [Run]. In the "Preferred Launcher" pane, pick "Remote Launching via TCF/TE Launcher." Click "Apply and Close." Click OK on the "Select Preferred Launcher" dialog. The Connection selection control has been updated to allow selection of connections created using the Connection toolbar.

Eclipse* based IDE (ISS-3026)	Switching between multiple remote target systems within a project does not always run the application on the correct target system.	When switching among multiple remote target systems within a project, the project does not always run on the correct target system.	1) Delete the target connection. 2) Create the target connection. 3) Run the project.
Eclipse* based IDE (ISS-3590)	Installation of Intel(R) System Studio 2020 Linux Host on a system where Intel System Studio 2019 is already installed removes the System Studio opencl-sdk symbolic link.	When loading the System Studio 2019 Eclipse* IDE, users will see the error message "Intel Code Builder for OpenCL API - Error!"	Re-create the symbolic link: sudo ln -s /etc/alternatives/opencl-intel-tools /opt/intel/system_studio_2019/opencl-sdk
Energy Analysis Plugin	Failure to build Intel® SoC Watch drivers on the target.	Users cannot run an Energy Analysis collection without manually installing the driver.	Users must follow the Preparing a Target Linux* System for Energy Analysis guide to install required drivers: https://software.intel.com/en-us/energy-analysis-user-guide-preparing-a-target-linux-system-for-energy-analysis
GNU* GDB	By default the "Function call history" is empty after enabling reverse debugging option.	The user cannot see any history in the Function call history window.	Send "record btrace pt" command manually once debugging is started from the Debugger Console window.
Intel® Data Analytics Acceleration Library	Intel® Data Analytics Acceleration Library Python API (a.k.a. pyDAAL) is provided as source.	When building it on Windows, users may see warning messages.	Ignore the warnings, the messages do not indicate critical issues and do not affect the library's functionality.
OpenCL™ Tools	The OpenCL™ CPU Kernel Debugger feature in this release of OpenCL™ Tools requires the latest update of Intel® CPU Runtime for OpenCL™ Tools, available for Linux* and Microsoft Windows* OSes.		For more information, please see OpenCL™ Tools Release Notes and for any questions, see the OpenCL* Support Forum .
OpenCL™ Tools	OpenCL SDK doesn't support SUSE Linux Enterprise Server*		
OpenCL™ Tools	FPGA support was deprecated and removed from Intel® SDK for OpenCL™ - Offline Compiler.		Please use Intel® SDK for OpenCL™ Applications 2020 Update 1 if you need this functionality or Intel® FPGA SDK for OpenCL™.
How-to-Code Samples	How-to-code samples may not work for all target operating systems.	Samples might not compile for all target operating systems, resulting in build errors.	None. Updates to these samples will be made over the next weeks/months and will be dynamically available.

Samples (ISS-3620)	The Google mqtt C sample, the Hello world C sample, and the Hello world C++ sample are only supported using the "Docker Build Option."	Deselecting the Docker build option when creating a project from these samples may result in a project that cannot be built.	Select the "Docker Build Option" when building projects created from these samples.
Sensor Explorer (ISS-2504)	Using a right-click with the sensor explorer to remove sensors from Java* projects does not work.	Removing a sensor from a Java project by right-clicking the sensor and selecting 'Remove import(s) from current source file' may fail.	Use the checkbox provided to the left of each sensor to add/remove sensors from the project.
Sensor Support (ISS-2551)	The Sensor Support feature is not compatible with Java language projects in this release of System Studio.	Users are unable to use the Sensor Support view to add or remove sensors to Java projects.	Users can add or remove sensors to projects manually by editing the source code files and by appending the UPM Java package dependencies to the project's pom.xml file.
Sensor Support (ISSDEV-2783)	The Sensor Support feature is not compatible with Python language projects in this release of System Studio.	Users are unable to use the Sensor Support view to add or remove sensors to such projects and an error message is displayed when open.	Users can add or remove sensors to projects manually by editing the source code files and by appending the UPM Python module installation directory to the project's PYTHONPATH.
Visual Studio*	Installation of Intel System Studio with Microsoft Visual Studio* 2017 integration hangs and fails on some systems.	Installation may report errors or no errors, however, Visual Studio* 2017 integration is not installed.	For workaround options, see: https://software.intel.com/en-us/articles/intel-software-development-tools-integration-to-vs2017-issue
Yocto* compatible Linux* Platform Project Development	If the default browser is already open and Intel System Studio is installed as a root user, Toaster will not be launched in the default browser.	Users will be unable to configure their platform project via Toaster.	Close any running instance of the default browser before attempting to create a platform project in Intel System Studio, when Intel System Studio is installed as root.
Yocto* compatible Linux* Platform Project Development (ISS-3779)	<ISS_INSTALL_DIR>/YoctoProject/meta-intel-iss/recipes-socwatch/socwatch/intel-iss-socwatch-target.bb recipe creates symbolic link /lib64 -> /lib (or /lib32 -> /lib) by default, potentially causing a conflict if another recipe already created the /lib64 (or /lib32) directory.	Users will be unable to integrate SoC Watch into Yocto* Project images.	1) Remove the /lib64 -> /lib symlink If the build failure persists, 2.1) Create /lib64 folder if it does not exist. 2.2) Create symlink /lib64/ld-linux-x86-64.so.2 -> /lib/ld-linux-x86-64.so.2 if it does not exist.

7 Attributions

This product includes software developed at:

The Apache Software Foundation (<http://www.apache.org>).

Portions of this software were originally based on the following:

- software copyright (c) 1999, IBM Corporation., <http://www.ibm.com>.
- software copyright (c) 1999, Sun Microsystems., <http://www.sun.com>.
- the W3C consortium (<http://www.w3c.org>),
- the SAX project (<http://www.saxproject.org>)
- voluntary contributions made by Paul Eng on behalf of the Apache Software Foundation that were originally developed at iClick, Inc., software copyright (c) 1999.

This product includes updcrc macro,
Satchell Evaluations and Chuck Forsberg.
Copyright (C) 1986 Stephen Satchell.

This product includes software developed by the MX4J project
(<http://mx4j.sourceforge.net>).

This product includes ICU 1.8.1 and later.
Copyright (c) 1995-2006 International Business Machines Corporation and others.

Portions copyright (c) 1997-2007 Cypress Semiconductor Corporation.
All rights reserved.

This product includes XORP.
Copyright (c) 2001-2004 International Computer Science Institute

This product includes software from the book
"Linux Device Drivers" by Alessandro Rubini and Jonathan Corbet,
published by O'Reilly & Associates.

This product includes hashtab.c.
Bob Jenkins, 1996.

8 Notices and Disclaimers

Intel technologies may require enabled hardware, software or service activation.

No product or component can be absolutely secure.

Your costs and results may vary.

© Intel Corporation. Intel, the Intel logo, and other Intel marks are trademarks of Intel Corporation or its subsidiaries. Other names and brands may be claimed as the property of others.

Intel's compilers may or may not optimize to the same degree for non-Intel microprocessors for optimizations that are not unique to Intel microprocessors. These optimizations include SSE2, SSE3, and SSSE3 instruction sets and other optimizations. Intel does not guarantee the availability, functionality, or effectiveness of any optimization on microprocessors not manufactured by Intel. Microprocessor-dependent optimizations in this product are intended for use with Intel microprocessors. Certain optimizations not specific to Intel microarchitecture are reserved for Intel microprocessors. Please refer to the applicable product User and Reference Guides for more information regarding the specific instruction sets covered by this notice.

No license (express or implied, by estoppel or otherwise) to any intellectual property rights is granted by this document.

The products described may contain design defects or errors known as errata which may cause the product to deviate from published specifications. Current characterized errata are available on request.

Intel disclaims all express and implied warranties, including without limitation, the implied warranties of merchantability, fitness for a particular purpose, and non-infringement, as well as any warranty arising from course of performance, course of dealing, or usage in trade.

*Other names and brands may be claimed as the property of others

OpenCL and the OpenCL logo are trademarks of Apple Inc. used by permission by Khronos.