



Intel® Desktop Boards D845GRG and D845GBV Product Guide

Order Number: A84615-001

Revision History

Revision	Revision History	Date
-001	First release of the Intel® Desktop Boards D845GRG and D845GBV Product Guide.	April 2002

If an FCC declaration of conformity marking is present on the board, the following statement applies:

FCC Declaration of Conformity

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

For questions related to the EMC performance of this product, contact:

Intel Corporation
5200 N.E. Elam Young Parkway
Hillsboro, OR 97124
1-800-628-8686

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and the receiver.
- Connect the equipment to an outlet on a circuit other than the one to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Canadian Department of Communications Compliance Statement

This digital apparatus does not exceed the Class B limits for radio noise emissions from digital apparatus set out in the Radio Interference Regulations of the Canadian Department of Communications.

Le présent appareil numerique német pas de bruits radioélectriques dépassant les limites applicables aux appareils numériques de la classe B prescrites dans le Réglement sur le broullage radioélectrique édicté par le ministére des Communications du Canada.

Disclaimer

Information in this document is provided in connection with Intel® products. No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted by this document. Except as provided in Intel's Terms and Conditions of Sale for such products, Intel assumes no liability whatsoever, and Intel disclaims any express or implied warranty, relating to sale and/or use of Intel products including liability or warranties relating to fitness for a particular purpose, merchantability, or infringement of any patent, copyright or other intellectual property right. Intel products are not intended for use in medical, life saving, or life sustaining applications. Intel may make changes to specifications and product descriptions at any time, without notice.

Desktop Boards D845GRG and D845GBV may contain design defects or errors known as errata which may cause the product to deviate from published specifications. Current characterized errata are available on request.

Contact your local Intel sales office or your distributor to obtain the latest specifications and before placing your product order.

Copies of documents which have an ordering number and are referenced in this document, or other Intel literature, may be obtained from Intel Corporation by going to the World Wide Web site at: http://www.intel.com/ or by calling 1-800-548-4725.

Intel, Pentium, and Celeron are registered trademarks of Intel Corporation or its subsidiaries in the United States and other countries.

† Other names and brands may be claimed as the property of others.

Copyright © 2002, Intel Corporation. All rights reserved.

Contents

1 Desktop Board Features

Components 9
Processor 11
Main Memory 12
Intel® 845G Chipset 12
- Intel® 82845G Graphics Memory Controller Hub (GMCH) 13
- Intel® 82801DB I/O Controller Hub (ICH4) 13
- Firmware Hub (FWH) 13

Input/Output (I/O) Controller 13
Graphics Subsystem 14
Audio Subsystem 14
LAN Subsystem (Optional) 14
- LAN Subsystem Software 14
- RJ-45 LAN Connector LEDs 15

Hi-Speed USB 2.0 Support 15
Enhanced IDE Interface 15
Expansion Slots 16
- Accelerated Graphics Port (AGP) 16
- Communication and Networking Riser (CNR) (Optional) 16

BIOS 16
- PCI Auto Configuration 16
- IDE Auto Configuration 17
- Security Passwords 17

Power Management Features 17
- ACPI 17
- Suspend to RAM (Instantly Available PC Technology) 18

Hardware Management 19
- Power Connectors 19
- Fan Connectors 19
- Resume on Ring 19
- Wake from USB 19
- Wake from PS/2 Keyboard/Mouse 20
- PME# Wakeup Support 20

Speaker 20
Battery 20
Real-Time Clock 20

2 Installing and Replacing Desktop Board Components

Before You Begin 21
Installing the I/O Shield 22
Installing and Removing the Desktop Board 23
Installing and Removing a Processor 24
Installing a Processor 24
Installing the Processor Fan Heat Sink 24
Connecting the Processor Fan Heat Sink Cable 25
Removing the Processor 25
Installing and Removing Memory 26
Installing DIMMs 26
Removing DIMMs 27
Installing and Removing an AGP Card 27
Installing an AGP Card 27
Removing the AGP Card 28
Connecting the IDE Cable 28
Connecting the Front Panel Header 30
Setting the BIOS Configuration Jumper Block 30
Installing a Front Panel Audio Solution 31
Installing a Front Panel USB Solution 31
Clearing Passwords 32
Replacing the Battery 33

3 Updating the BIOS

Updating the BIOS with the Intel® Express BIOS Update Utility 37
Updating the BIOS with the Intel® Flash Memory Update Utility 38
Obtaining the BIOS Update File 38
Updating the BIOS 38
Recovering the BIOS 39

4 Using the BIOS Setup Program

Maintenance Menu 42
Main Menu 43
Advanced Menu 44
PCI Configuration Submenu 45
Boot Configuration Submenu 46
Peripheral Configuration Submenu 47
IDE Configuration Submenu 49
Primary/Secondary IDE Master/Slave Submenus 50
Diskette Configuration Submenu 51
Event Log Configuration Submenu 52
Video Configuration Submenu 53
USB Configuration Submenu 54
Chipset Configuration Submenu 55
Security Menu 56
Power Menu 57
ACPI Submenu 57

Boot Menu 58
Boot Device Priority Submenu 59
Hard Disk Drives Submenu 59
Removable Devices Submenu 60
ATAPI CD-ROM Drives 60
Exit Menu 61

5 Technical Reference

Board Connectors 63
Back Panel Connectors 64
Midboard Connectors 65
Audio Connectors 65
Power and Hardware Connectors 66
Add-In Card and Peripheral Interface Connectors 67
Front Panel Headers 68
Desktop Board Resources 70
Memory Map 70
DMA Channels 70
Interrupts 71

A Error Messages and Indicators

BIOS Beep Codes 73
BIOS Error Messages 74

B Regulatory Compliance

Safety Regulations 77
EMC Regulations 77
Product Certification Markings 78
Installation Precautions 79
Installation Instructions 79
Ensure Electromagnetic Compatibility (EMC) Compliance 79
Chassis and Component Certifications 80
Prevent Power Supply Overload 80
Place Battery Marking 80
Use Only for Intended Applications 80

Figures

1. Desktop Board D845GRG Components 9
2. Desktop Board D845GBV Components 10
3. Location of Standby Power Indicator 18
4. Installing the I/O Shield 22
5. Desktop Board D845GBV Mounting Holes 23
6. Installing a Processor 24
7. Connecting the Processor Fan Heat Sink Cable to the Processor Fan Connector 25
8. Installing a Memory Module 26
9. Removing the AGP Card 28
10. Connecting the IDE Cable 29
11. Location of the BIOS Configuration Jumper Block 30

12. Removing the Battery 35
13. Back Panel Connectors 64
14. Audio Connectors 65
15. Power and Hardware Control Connectors....66
16. Desktop Board D845GBV Add-in Card and Peripheral Interface Connectors 67
17. Front Panel Headers....68

Tables

1. Feature Summary 7
2. Supported Processors 11
3. RJ-45 LAN Connector LEDs 15
4. Jumper Settings for the BIOS Setup Program Modes (J9H2) 30
5. BIOS Setup Program Menu Bar....41
6. BIOS Setup Program Function Keys....42
7. Maintenance Menu 42
8. Main Menu....43
9. Advanced Menu....44
10. PCI Configuration Submenu 45
11. Boot Configuration Submenu....46
12. Peripheral Configuration Submenu 47
13. IDE Configuration Submenu 49
14. Primary/Secondary IDE Master/Slave Submenus....50
15. Diskette Configuration Submenu 51
16. Event Log Configuration Submenu 52
17. Video Configuration Submenu 53
18. USB Configuration Submenu....54
19. Chipset Configuration Submenu 55
20. Security Menu....56
21. Power Menu....57
22. ACPI Submenu....57
23. Boot Menu 58
24. Boot Device Priority Submenu 59
25. Hard Disk Drives Submenu....59
26. Removable Devices Submenu....60
27. ATAPI CD-ROM Drives Submenu....60
28. Exit Menu....61
29. Front Panel Audio Header Signal Names (J8A1) 65
30. Front Panel USB 2.0 Header (J9F1) 68
31. Front Panel Header (J9G1)....69
32. System Memory Map....70
33. DMA Channels....70
34. Interrupts 71
35. Beep Codes....73
36. BIOS Error Messages....74
37. Safety Regulations....77
38. EMC Regulations....77

1 Desktop Board Features

NOTE

The Intel® Desktop Board D845GRG layout was used for illustrations unless otherwise noted.

Table 1 describes the major features of Intel® Desktop Boards D845GRG and D845GBV.

Table 1. Feature Summary

Form Factors	• microATX at 9.6 inches by 8.2 inches (Desktop Board D845GRG) • ATX at 12.0 inches by 8.2 inches (Desktop Board D845GBV)
Processor	Support for: • 533/400 MHz front side bus (FSB) Intel® Pentium® 4 processor in an mPGA-478 socket • 400 MHz FSB Intel® Celeron® processor in an mPGA-478 socket
Memory	• Two 184-pin, 2.5 V SDRAM Dual Inline Memory Module (DIMM) sockets • 266/200 MHz DDR SDRAM interface • Designed to support up to 2 GB of system memory **NOTE:** *Desktop Boards D845GRG and D845GBV have been designed to support DIMMs based on 512 Mbit technology up to 2 GB, but this technology has not been validated on these Intel desktop boards. For more information about the latest list of tested memory, refer to the Intel World Wide Web site at:* http://support.intel.com/support/motherboards/desktop/
Chipset	• Intel® 845G chipset consisting of: • Intel® 82845G Graphics Memory Controller Hub (GMCH) with Accelerated Hub Architecture (AHA) bus • Intel® 82801DB I/O Controller Hub (ICH4) with support for up to six Hi-Speed Universal Serial Bus 2.0 (USB 2.0) ports • 4 Mbit Firmware Hub (FWH)
I/O Control	Support for: • SMSC LPC47M172 • National Semiconductor PC87372
Graphics	• Intel 845G chipset • Integrated Intel® Extreme Graphics • 1.5 V AGP connector • Single AGP port via the connector or integrated graphics • AGP 2.0 including 1x/2x/4x AGP data transfers and 2x/4x Fast Writes • 350 MHz AGP Digital Display (ADD) interface cards • Digital Video Output (DVO) port
Audio	• Intel 845G chipset (AC '97) • Analog Devices Inc. audio codec

continued

Table 1. Feature Summary (continued)

LAN (optional)	• Intel® 82562ET 10/100 Mbit/sec Platform LAN Connect (PLC) device and RJ-45 connector
Peripheral Interfaces	• Up to six USB 2.0 ports — Four ports routed to the back panel — Two ports routed to the front panel USB header • Two IDE interfaces with Ultra DMA-33 and ATA-66/100 support • One diskette drive interface • One parallel port • Two serial ports (one via a board header) • PS/2† keyboard and mouse ports
Expansion Capabilities	• Desktop Board D845GRG: — Three PCI bus add-in card connectors — One AGP connector — One optional Communication and Networking Riser (CNR) connector (slot shared with PCI bus connector 3) • Desktop Board D845GBV: — Six PCI bus add-in card connectors — One AGP connector — One optional CNR connector (slot shared with PCI bus connector 6)
BIOS	• Intel/AMI BIOS • 4 Mbit symmetrical flash memory • Support for SMBIOS
Power Management	• Support for Advanced Configuration and Power Interface (ACPI) • Suspend to RAM (STR) support • Wake on USB, PCI, CNR, RS-232, PS/2, LAN, and front panel
Hardware Management	Hardware monitor with: • Two fan sensing inputs used to monitor fan activity • Remote diode temperature sensing • Voltage sensing to detect out of range values

NOTE

For information about Intel® desktop boards, including technical product specifications, BIOS updates, and device drivers, go to the Intel World Wide Web site at:

http://support.intel.com/support/motherboards/desktop/

Components

Figure 1 shows the location of the major components on Desktop Board D845GRG.



A	Audio codec	P	Primary IDE connector
B	Front panel audio header	Q	Speaker
C	Auxiliary line-in connector (ATAPI)	R	Battery
D	Rear chassis fan connector (tachometer input)	S	SCSI hard drive activity LED connector
E	CD-ROM connector (ATAPI)	T	Alternate power/sleep LED header
F	Back panel connectors	U	Chassis intrusion connector
G	12 V processor core voltage connector	V	Front chassis fan connector
H	Intel 82845G (GMCH)	W	BIOS configuration jumper
I	Processor socket	X	Front panel header
J	Processor fan connector (tachometer input)	Y	Intel 82801DB (ICH4)
K	DIMM sockets	Z	Front panel USB 2.0 header
L	Super I/O controller	AA	AGP connector
M	Main power connector	BB	PCI bus add-in card connectors
N	Diskette drive connector	CC	CNR (optional)
O	Secondary IDE connector		

Figure 1. Desktop Board D845GRG Components

Figure 2 shows the location of the major components on Desktop Board D845GBV.



A	Audio codec	P	Primary IDE connector
B	Front panel audio header	Q	Speaker
C	Auxiliary line-in connector (ATAPI)	R	Battery
D	Rear chassis fan connector (tachometer input)	S	SCSI hard drive activity LED connector
E	CD-ROM connector (ATAPI)	T	Alternate power/sleep LED header
F	Back panel connectors	U	Chassis intrusion connector
G	12 V processor core voltage connector	V	Front chassis fan connector
H	Intel 82845G (GMCH)	W	BIOS configuration jumper
I	Processor socket	X	Front panel header
J	Processor fan connector (tachometer input)	Y	Intel 82801DB (ICH4)
K	DIMM sockets	Z	Front panel USB header
L	Super I/O controller	AA	AGP connector
M	Power connector	BB	PCI bus add-in card connectors
N	Diskette drive connector	CC	CNR (optional)
O	Secondary IDE connector		

Figure 2. Desktop Board D845GBV Components

Processor

⚠ CAUTION

Failure to use an ATX12V power supply, or not connecting the additional power supply lead to Desktop Board D845GRG or D845GBV may result in damage to the desktop board and/or power supply.

Desktop Boards D845GRG and D845GBV support a single Intel Pentium 4 processor or Intel Celeron processor. Processors are not included with the desktop board and must be purchased separately.

The processor connects to the Intel desktop board through the mPGA478-pin socket. The Intel Pentium 4 processor and Intel Celeron processor may be removed and replaced to accommodate supported higher speed processors.

Desktop Boards D845GRG and D845GBV support the processors listed in Table 2.

Table 2. Supported Processors

Type	Designation	Front Side Bus Frequency	L2 Cache
Intel Pentium 4 processor on .13 micron process in an mPGA-478 package	2.40B and 2.26 GHz	533 MHz	512 KB
Intel Pentium 4 processor on .13 micron process in an mPGA-478 package	2.40, 2.20A, 2A, 1.80A, and 1.60A GHz	400 MHz	512 KB
Intel Pentium 4 processor on .18 micron process in an mPGA-478 package	2, 1.90, 1.80, 1.70, 1.60, and 1.50 GHz	400 MHz	256 KB
Intel Celeron processor in an mPGA-478 package	1.8 and 1.7 GHz	400 MHz	128 KB

For the latest information on processor support for Desktop Boards D845GRG and D845GBV, refer to the Intel World Wide Web site at:

http://support.intel.com/support/motherboards/desktop/

For instructions on installing or upgrading the processor, see Chapter 2 on page 21.

Desktop Boards D845GRG and D845GBV require an ATX12V compliant power supply to function according to desktop board specifications. Both boards have two ATX12V compliant power supply connectors that are needed to provide extra power to the Intel 845G chipset and Intel Pentium 4 processor or Intel Celeron processor.

Items B and D in Figure 15 on page 66 show the two power connector locations.

Main Memory

NOTE

To be fully compliant with all applicable Intel® SDRAM memory specifications, the board should be populated with DIMMs that support the Serial Presence Detect (SPD) data structure. If your memory modules do not support SPD, you will see a notification to this effect on the screen at power up. The BIOS will attempt to configure the memory controller for normal operation.

Desktop Boards D845GRG and D845GBV support system memory as defined below:

- Up to two 184-pin DDR SDRAM Dual Inline Memory Modules (DIMMs) with gold-plated contacts
- DDR266 and DDR200 SDRAM
- Unbuffered and non-registered single or double-sided DIMMs
- Serial Presence Detect (SPD) memory
- Non-ECC and ECC DIMMs
- 2.5 V memory only
- 64 Mbit, 128 Mbit, 256 Mbit, and 512 Mbit technologies for the following memory configurations:
  - 64 MB (minimum)
  - 256 MB (64 Mbit technology)
  - 512 MB (128 Mbit technology)
  - 1024 MB (256 Mbit technology)
  - 2048 MB (512 Mbit technology)

NOTE

Desktop Boards D845GRG and D845GBV have been designed to support DIMMs based on 512 Mbit technology up to 2 GB, but this technology has not been validated on these Intel desktop boards. For more information about the latest list of tested memory, refer to the Intel World Wide Web site at:

http://support.intel.com/support/motherboards/desktop/

All memory components and DIMMs used with the Intel desktop boards must comply with the PC SDRAM specifications. You can access these documents through the World Wide Web at:

http://www.intel.com/technology/memory/pcsdram/spec/

For information about installing memory, see Chapter 2 starting on page 21.

Intel® 845G Chipset

The Intel 845G chipset consists of the following devices:

- Intel 82845G Graphics Memory Controller Hub (GMCH) with AHA bus
- Intel 82801DB I/O Controller Hub (ICH4) with AHA bus
- Firmware Hub (FWH)

Intel® 82845G Graphics Memory Controller Hub (GMCH)

The GMCH provides the processor, system memory, AGP, and hub interfaces in the Intel 845 chipset platform. Features on Desktop Boards D845GRG and D845GBV include:

- Single processor support with 533 MHz or 400 MHz data transfer rates
- Support for up to 2 GB (with 512 Mbit technology) DDR-SDRAM at 266/200 MHz operation

NOTE

512 Mbit technology has not been validated on these boards

- 1.5 V AGP interface with 4X Side Band Addressing (SBA)/data transfer and 2X and 4X fast write

Intel® 82801DB I/O Controller Hub (ICH4)

The ICH4 integrates many I/O functions and provides the I/O subsystem with access to the rest of the platform. ICH4 features on Desktop Boards D845GRG and D845GBV include:

- Integrated IDE controller supports two Ultra DMA-33 and ATA-66/100 channels, and PIO modes
- SMBus interface
- FWH interface
- Low Pin Count (LPC) interface
- AC '97 2.1 compliant link for audio and telephony codecs
- Integrated Intel 82562ET 10/100 Mbit/sec Platform LAN Connect (PLC) device for interfacing the ICH4 LAN connect interface to LAN connect component
- Three UHCI and one EHCI compliant host controllers with support for up to six USB ports

Firmware Hub (FWH)

The 4 Mbit Firmware Hub has these features:

- System BIOS
- System security and management logic

Input/Output (I/O) Controller

The SMSC LPC47M172 or National Semiconductor PC87372 super I/O controllers feature the following:

- Low pin count (LPC) interface
- Two serial ports (one via a board connector)
- One parallel port with Extended Capabilities Port (ECP) and Enhanced Parallel Port (EPP) support
- Serial IRQ interface compatible with serialized IRQ support for PCI systems
- PS/2-style mouse and keyboard interfaces
- Interface for one 1.2 MB, 1.44 MB, or 2.88 MB diskette drive
- Intelligent power management, including a programmable wake up event interface
- PCI power management support
- Two fan tachometer inputs

Graphics Subsystem

The graphics subsystem features the following:

- Intel 845G chipset
- Intel Extreme Graphics
- 1.5 V AGP connector

Audio Subsystem

The audio subsystem features the following:

- Intel 845G chipset (AC '97)
- Analog Devices Inc. AD1981A audio codec

NOTE

The line out connector, located on the back panel, is designed to power either headphones or amplified speakers only. Poor audio quality may occur if passive (non-amplified) speakers are connected to this output.

Audio drivers and utilities are available from Intel's World Wide Web site:

http://support.intel.com/support/motherboards/desktop/

LAN Subsystem (Optional)

The optional Intel 82562ET (with the Intel 82801DB ICH4) provides a Fast PCI LAN subsystem providing both 10Base-T and 100Base-TX connectivity. The Intel 82562ET provides the following functions:

- Basic 10/100 Ethernet LAN connectivity
- Supports RJ-45 connector with status indicator LEDs
- Programmable transit threshold
- Configurable EEPROM that contains the MAC address

LAN Subsystem Software

For LAN software and drivers, refer to the D845GRG or D845GBV link on Intel's World Wide Web site at:

http://support.intel.com/support/motherboards/desktop

RJ-45 LAN Connector LEDs

Two LEDs are built into the RJ-45 LAN connector. Table 3 describes the LED states when the board is powered up and the LAN subsystem is operating.

Table 3. RJ-45 LAN Connector LEDs

LED Color	LED State	Indicates
Green	Off	10 Mbit/sec data rate is selected.
	On	100 Mbit/sec data rate is selected.
Yellow	Off	LAN link is not established.
	On (steady state)	LAN link is established.
	On (brighter and pulsing)	The computer is communicating with another computer on the LAN.

Hi-Speed USB 2.0 Support

NOTE

Computer systems that have an unshielded cable attached to a USB port might not meet FCC Class B requirements, even if no device or a low-speed USB device is attached to the cable. Use a shielded cable that meets the requirements for a full-speed USB device.

These Intel desktop boards support up to six USB 2.0 ports via ICH4; four ports routed to the back panel and two routed to a USB front panel header. USB 2.0 ports are backward compatible with USB 1.1 devices. USB 1.1 devices will function normally at USB 1.1 speeds.

USB 2.0 support requires both an operating system and drivers that fully support USB 2.0 transfer rates. Disabling Hi-Speed USB in BIOS reverts all USB 2.0 ports to USB 1.1 operation. This may be required to accommodate operating systems that do not support USB 2.0.

NOTE

USB devices are limited to USB 1.1 transfer rates prior to operating system and driver initialization.

Enhanced IDE Interface

The ICH4's IDE interface handles the exchange of information between the processor and peripheral devices like hard disks, CD-ROM drives, and Iomega Zip† drives inside the computer. The interface supports:

- Up to four IDE devices (such as hard drives)
- ATAPI devices (such as CD-ROM drives)
- Older PIO Mode devices
- Ultra DMA-33 and ATA-66/100 protocols
- Laser servo (LS-120) drives

Expansion Slots

Desktop Boards D845GRG and D845GBV have the following add-in card connectors:

Desktop Board D845GRG has:

- Three PCI bus add-in card connectors (SMBus routed to PCI bus connector 2)
- One AGP connector
- One optional CNR connector (slot shared with PCI bus connector 3)

Desktop Board D845GBV has:

- Six PCI bus add-in card connectors (SMBus routed to PCI bus connector 2)
- One AGP connector
- One optional CNR connector (slot shared with PCI bus connector 6)

Accelerated Graphics Port (AGP)

NOTE

Desktop Boards D845GRG and D845GBV are only compatible with 1.5 V AGP cards.

AGP is a high-performance interface for graphics-intensive applications, such as 3D graphics. AGP is independent of the PCI bus and is intended for exclusive use with graphical display devices.

The AGP connector supports 1.5 V AGP 4X and 2X add-in cards.

Communication and Networking Riser (CNR) (Optional)

The optional CNR provides an interface that supports various features such as audio, modem, USB, and LAN.

BIOS

The BIOS provides the Power-On Self-Test (POST), the BIOS Setup program, the PCI and IDE auto-configuration utilities, and the video BIOS. The BIOS is stored in the Firmware Hub.

The BIOS can be updated by following the instructions in Chapter 3 on page 37.

PCI Auto Configuration

If you install a PCI add-in card in your computer, the PCI auto-configuration utility in the BIOS automatically detects and configures the resources (IRQs, DMA channels, and I/O space) for that add-in card. You do not need to run the BIOS Setup program after you install a PCI add-in card.

IDE Auto Configuration

If you install an IDE device (such as a hard drive) in your computer, the IDE auto-configuration utility in the BIOS automatically detects and configures the device for your computer. You do not need to run the BIOS Setup program after installing an IDE device. You can override the auto-configuration options by specifying manual configuration in the BIOS Setup program.

To use ATA-66/100 features, the following items are required:

- An ATA-66/100 peripheral device
- An ATA-66/100 compatible cable
- ATA-66/100 operating system device drivers

Security Passwords

The BIOS includes security features that restrict whether the BIOS Setup program can be accessed and who can boot the computer. A supervisor password and a user password can be set for the Setup and for booting the computer, with the following restrictions:

- The supervisor password gives unrestricted access to view and change all Setup options. If only the supervisor password is set, pressing <Enter> at the password prompt of Setup gives the user restricted access to Setup.
- If both the supervisor and user passwords are set, you must enter either the supervisor password or the user password to access Setup. Setup options are then available for viewing and changing depending on whether the supervisor or user password was entered.
- Setting a user password restricts who can boot the computer. The password prompt is displayed before the computer is booted. If only the supervisor password is set, the computer boots without asking for a password. If both passwords are set, you can enter either password to boot the computer.

Power Management Features

Power management is implemented at several levels, including:

- Advanced Configuration and Power Interface (ACPI)
- Suspend to RAM (Instantly Available PC technology)

ACPI

ACPI gives the operating system direct control over the power management and Plug & Play functions of a computer. The use of ACPI with Desktop Board D845GRG or D845GBV requires an operating system that provides full ACPI support.

Suspend to RAM (Instantly Available PC Technology)

CAUTION

For Instantly Available PC technology, the 5 V standby line for the power supply must be capable of delivering adequate +5 V standby current. Failure to provide adequate standby current when using this feature can damage the power supply and/or effect ACPI S3 sleep state functionality.

Instantly Available technology enables the board to enter the ACPI S3 (Suspend-to-RAM) sleep state. While in the S3 sleep state, the computer will appear to be off. When signaled by a wake-up device or event, the system quickly returns to its last known awake state.

The Intel desktop board's standby power indicator, shown in Figure 3, is lit when there is standby power to the system. This includes the memory modules and PCI bus connectors, even when the computer appears to be off.

If the system has a dual-colored power LED on the front panel, the sleep state is indicated by the LED turning amber.



Figure 3. Location of Standby Power Indicator

CAUTION

Power supplies used with this board must be able to provide enough standby current to support the standard Instantly Available (ACPI S3 sleep state) configuration. If the standby current necessary to support multiple wake events from the PCI and/or USB buses exceeds power supply capacity, the Intel desktop board may lose register settings stored in memory.

For more information on standby current requirements for these desktop boards, refer to the TPS by selecting the Technical Documentation link at:

http://developer.intel.com/design/motherbd/

Hardware Management

- Power connectors
- Fan connectors
- Resume on Ring
- Wake from USB
- Wake from PS/2 keyboard/mouse
- PME# wakeup support

Power Connectors

Desktop Boards D845GRG and D845GBV have two power connectors. See Figure 15 on page 66 for the location of the power connectors.

Fan Connectors

Desktop Boards D845GRG and D845GBV have two chassis fan connectors and one processor fan connector. See Figure 15 on page 66 for the location of the fan connectors.

Resume on Ring

The operation of Resume on Ring can be summarized as follows:

- Resumes operation from either ACPI S1 or ACPI S3 state
- Requires only one call to access the computer
- Detects incoming call similarly for external and internal modems
- Requires modem interrupt be unmasked for correct operation

Wake from USB

USB bus activity wakes the computer from an ACPI S1 or S3 state.

NOTE

Wake from USB requires the use of a USB peripheral that supports Wake from USB.

Wake from PS/2 Keyboard/Mouse

PS/2 keyboard/mouse activity wakes the computer from an ACPI S1 or S3 state.

PME# Wakeup Support

When the PME# signal on the PCI bus is asserted, the computer wakes from an ACPI S1, S3, or S5 state.

Speaker

A speaker is mounted on the desktop board. The speaker provides audible error code (beep code) information during the Power-On Self-Test (POST).

Battery

A battery on the Intel desktop board keeps the values in CMOS RAM and the clock current when the computer is turned off. See Chapter 2 starting on page 21 for instructions on how to replace the battery.

Real-Time Clock

Desktop Boards D845GRG and D845GBV have a time-of-day clock and 100-year calendar. A battery on the desktop board keeps the clock current when the computer is turned off.

2 Installing and Replacing Desktop Board Components

This chapter tells you how to:

- Install the I/O shield
- Install and remove the desktop board
- Install and remove a processor
- Install and remove memory
- Install and remove an AGP card
- Connect the IDE cable
- Connect the front panel header
- Set the BIOS jumper
- Install the front panel audio solution
- Install the front panel USB solution
- Clear passwords
- Replace the battery

Before You Begin

⚠ CAUTION

Before you install this board in a chassis, see Appendix B for regulatory requirements and precautions.

- *Always follow the steps in each procedure in the correct order.*
- *Set up a log to record information about your computer, such as model, serial numbers, installed options, and configuration information.*
- *Electrostatic discharge (ESD) can damage components. Perform the procedures described in this chapter only at an ESD workstation using an antistatic wrist strap and a conductive foam pad. If such a station is not available, you can provide some ESD protection by wearing an antistatic wrist strap and attaching it to a metal part of the computer chassis.*

⚠ WARNINGS

The procedures in this chapter assume familiarity with the general terminology associated with personal computers and with the safety practices and regulatory compliance required for using and modifying electronic equipment.

Disconnect the computer from its power source and from any telecommunications links, networks, or modems before performing any of the procedures described in this chapter. Failure to disconnect power, telecommunications links, networks, or modems before you open the computer or perform any procedures can result in personal injury or equipment damage. Some circuitry on the board can continue to operate even though the front panel power button is off.

Installing the I/O Shield

The Intel desktop board comes with an I/O shield. When installed in the chassis, the shield blocks radio frequency transmissions, protects internal components from dust and foreign objects, and promotes correct airflow within the chassis.

Install the I/O shield before installing the desktop board in the chassis. Place the shield inside the chassis as shown in Figure 4. Press the shield into place so that it fits tightly and securely. If the shield doesn't fit, obtain a properly-sized shield from the chassis supplier.



Figure 4. Installing the I/O Shield

Installing and Removing the Desktop Board

Refer to your chassis manual for instructions on installing and removing the Intel desktop board.

WARNING

This procedure should be done only by qualified technical personnel. Disconnect the computer from its power source before performing the procedures described here. Failure to disconnect the power before you open the computer can result in personal injury or equipment damage.

NOTES

You will need a Phillips† (#2 bit) screwdriver.

Refer to Appendix B for regulatory requirements and installation instructions and precautions.

Figure 5 shows the location of the eight mounting holes for Desktop Board D845GBV. Desktop Board D845GRG has six mounting holes.



Figure 5. Desktop Board D845GBV Mounting Holes

Installing and Removing a Processor

Instructions on how to install the processor to the Intel desktop board are given below.

Installing a Processor

⚠ CAUTION

Before installing or removing the processor, make sure that AC power has been removed by unplugging the power cord from the computer; the standby power LED should not be lit (see Figure 3 on page 18). Failure to do so could damage the processor and the board.

To install a processor, follow these instructions:

1. Observe the precautions in "Before You Begin" on page 21.
2. Locate the processor socket and raise the socket lever completely.
3. Install the processor so that the corner with the triangle marking (A) is aligned with the corner where the lever is attached to the socket (see Figure 6).
4. Lower the lever to its original position.



Figure 6. Installing a Processor

Installing the Processor Fan Heat Sink

Desktop Boards D845GRG and D845GBV have an integrated processor fan heat sink retention mechanism (RM). For instructions on how to install the processor fan heat sink to the integrated processor fan heat sink RM, refer to the boxed processor manual or the Intel World Wide Web site at:

http://support.intel.com/support/processors/pentium4/intnotes478.htm

Connecting the Processor Fan Heat Sink Cable

Connect the processor fan heat sink cable to the processor fan connector (see Figure 7).



Figure 7. Connecting the Processor Fan Heat Sink Cable to the Processor Fan Connector

Removing the Processor

For instruction on how to remove the processor fan heat sink and processor, refer to the processor installation manual or the Intel World Wide Web site at:

http://support.intel.com/support/processors/pentium4/intnotes478.htm

Installing and Removing Memory

CAUTION

To be fully compliant with all applicable Intel SDRAM memory specifications, the boards require DIMMs that support the Serial Presence Detect (SPD) data structure.

You can access the PC Serial Presence Detect Specification at:

http://www.intel.com/technology/memory/pcsdram/spec/

Desktop Boards D845GRG2 and D845GBV have two 184-pin DIMM sockets arranged as banks 0 and 1, as shown in Figure 8. If installing a single DIMM, install it in bank 0.

Refer to the Main Memory heading on page 12 for memory requirements.

Installing DIMMs

CAUTION

Install memory in the DIMM sockets prior to installing the AGP video card to avoid interference with the memory retention mechanism.

To install DIMMs, follow these steps:

1. Observe the precautions in "Before You Begin" on page 21.
2. Turn off all peripheral devices connected to the computer. Turn off the computer and disconnect the AC power cord.
3. Remove the computer's cover and locate the DIMM sockets (see Figure 8).
4. Remove the AGP video card if it interferes with the DIMM clips from being easily opened and closed.



Figure 8. Installing a Memory Module

5. Make sure the clips at either end of the DIMM socket(s) are pushed outward to the open position.
6. Holding the DIMM by the edges, remove it from its anti-static package.
7. Position the DIMM above the socket. Align the two small notches in the bottom edge of the DIMM with the keys in the socket (see inset in Figure 8).
8. Insert the bottom edge of the DIMM into the socket.
9. When the DIMM is inserted, push down on the top edge of the DIMM until the retaining clips snap into place. Make sure the clips are firmly in place.
10. Reinstall the AGP card if it was removed prior to installing the DIMMs.
11. Replace the computer's cover and reconnect the AC power cord.

Removing DIMMs

To remove a memory module, follow these steps:

1. Observe the precautions in "Before You Begin" on page 21.
2. Turn off all peripheral devices connected to the computer. Turn off the computer.
3. Remove the AC power cord from the computer.
4. Remove the computer's cover.
5. Remove the AGP card if it interferes with the DIMM clips from being easily opened and closed.
6. Gently spread the retaining clips at each end of the DIMM socket. The DIMM pops out of the socket.
7. Hold the DIMM by the edges, lift it away from the socket, and store it in an anti-static package.
8. Reinstall the AGP card if you removed it before installing the DIMMs.
9. Reinstall and reconnect any parts you removed or disconnected to reach the DIMM sockets.
10. Replace the computer's cover and reconnect the AC power cord.

Installing and Removing an AGP Card

The AGP connector supports 1.5 V 4X and 2X AGP cards. Intel desktop boards have an integrated AGP card retention mechanism (RM).

Installing an AGP Card

Follow these instructions to install an AGP card:

1. Place the AGP card in the AGP connector.
2. Press down on the card until it is completely seated in the AGP connector and the card retention notch snaps into place around the RM pin.
3. Secure the card's metal bracket to the chassis back panel with a screw.

Removing the AGP Card

Follow these instructions to remove the AGP card from the RM:

1. Remove the screw (B) that secures the card's metal bracket (A) to the chassis back panel.
2. Push back on the RM lever (D), as shown in Figure 9, until the retention pin (C) completely clears the notch in the card.
3. Pull the card straight up (E).



Figure 9. Removing the AGP Card

Connecting the IDE Cable

The Intel® boxed desktop board package includes an IDE cable. The cable connects two drives to the desktop board. The cable supports the Ultra DMA-33 and ATA-66/100 transfer protocols. Figure 10 shows the correct installation of the cable.

NOTE

ATA-66/100 compatible cables are backward compatible with drives using slower IDE transfer protocols. If an ATA-66/100 disk drive and a disk drive using any other IDE transfer protocol are attached to the same cable, the maximum transfer rate between the drives may be reduced to that of the slowest drive.

NOTE

Do not connect an ATA device as a slave on the same IDE cable as an ATAPI master device. For example, do not connect an ATA hard drive as a slave to an ATAPI CD-ROM drive.

For correct function of the cable:

- Attach the cable end with the single connector to the Intel desktop board.
- Attach the cable end with the two closely spaced connectors to the drives.



Figure 10. Connecting the IDE Cable

Connecting the Front Panel Header

Before connecting the front panel header, observe the precautions in "Before You Begin" on page 21. Refer to Table 31 on page 69 for pin assignments.

Setting the BIOS Configuration Jumper Block

CAUTION

Always turn off the power and unplug the power cord from the computer before changing the jumper. Moving the jumper with the power on may result in unreliable computer operation.

The location of the Intel desktop board's BIOS configuration jumper is shown in Figure 11.



Figure 11. Location of the BIOS Configuration Jumper Block

The three-pin BIOS jumper block enables all board configurations to be done in BIOS Setup. Table 4 shows the jumper settings for the Setup program modes.

Table 4. Jumper Settings for the BIOS Setup Program Modes (J9H2)

Jumper Setting	Mode	Description
3 1	Normal (default) (1-2)	The BIOS uses the current configuration and passwords for booting.
3 1	Configure (2-3)	After the Power-On Self-Test (POST) runs, the BIOS displays the Maintenance Menu. Use this menu to clear passwords.
3 1	Recovery (None)	The BIOS recovers data from a recovery diskette in the event of a failed BIOS update.

Installing a Front Panel Audio Solution

To install the cable that connects the front panel audio solution to the front panel audio header, follow these steps:

1. Observe the precautions in "Before You Begin" on page 21.
2. Turn off all peripheral devices connected to the computer. Turn off the computer and disconnect the AC power cord.
3. Remove the cover.
4. Locate the front panel audio header (J8A1), see Figure 14 on page 65.
5. Remove the two jumpers from the header to disable the back panel audio connectors.
6. Install a correctly keyed and shielded front panel audio cable.
7. Connect the audio cable to the front panel audio solution.
8. Replace the cover.

To restore back panel operations, follow these steps:

1. Observe the precautions in "Before You Begin" on page 21.
2. Turn off all peripheral devices connected to the computer. Turn off the computer and disconnect the AC power cord.
3. Remove the cover.
4. Remove the front panel audio cable.
5. Install a jumper on pins 5-6 (rear R channel).
6. Install a jumper on pins 9-10 (rear L channel).
7. Replace the cover.

Installing a Front Panel USB Solution

Before installing a front panel USB 2.0 solution, observe the precautions in "Before You Begin" on page 21. Refer to Table 30 on page 68 for pin assignments.

Clearing Passwords

This procedure assumes that the board is installed in the computer and the configuration jumper block is set to normal mode.

1. Observe the precautions in "Before You Begin" on page 21.
2. Turn off all peripheral devices connected to the computer. Turn off the computer. Disconnect the computer's power cord from the AC power source (wall outlet or power adapter).
3. Remove the computer cover.
4. Find the configuration jumper block (see Figure 11).
5. Place the jumper on pins 2-3 as shown below.

6. Replace the cover, plug in the computer, turn on the computer, and allow it to boot.
7. The computer starts the Setup program. Setup displays the maintenance menu.
8. Use the arrow keys to select Clear Passwords. Press <Enter> and Setup displays a pop-up screen requesting that you confirm clearing the password. Select Yes and press <Enter>. Setup displays the maintenance menu again.
9. Press <F10> to save the current values and exit Setup.
10. Turn off the computer. Disconnect the computer's power cord from the AC power source.
11. Remove the computer cover.
12. To restore normal operation, place the jumper on pins 1-2 as shown below.

13. Replace the cover, plug in the computer, and turn on the computer.

Replacing the Battery

A coin-cell battery (CR2032) powers the real-time clock and CMOS memory. When the computer is not plugged into a wall socket, the battery has an estimated life of three years. When the computer is plugged in, the standby current from the power supply extends the life of the battery. The clock is accurate to ± 13 minutes/year at 25 ºC with 3.3 VSB applied.

When the voltage drops below a certain level, the BIOS Setup program settings stored in CMOS RAM (for example, the date and time) might not be accurate. Replace the battery with an equivalent one. Figure 12 on page 35 shows the location of the battery.

⚠ CAUTION

Risk of explosion if the battery is replaced with an incorrect type. Batteries should be recycled where possible. Disposal of used batteries must be in accordance with local environmental regulations.

⚠ PRECAUTION

Risque d'explosion si la pile usagée est remplacée par une pile de type incorrect. Les piles usagées doivent être recyclées dans la mesure du possible. La mise au rebut des piles usagées doit respecter les réglementations locales en vigueur en matière de protection de l'environnement.

(French)

⚠ FORHOLDSREGEL

Eksplosionsfare, hvis batteriet erstattes med et batteri af en forkert type. Batterier bør om muligt genbruges. Bortskaffelse af brugte batterier bør foregå i overensstemmelse med gældende miljølovgivning.

(Danish)

⚠ OBS!

Det kan oppstå eksplosjonsfare hvis batteriet skiftes ut med feil type. Brukte batterier bør kastes i henhold til gjeldende miljølovgivning.

(Norwegian)

⚠ VIKTIGT!

Risk för explosion om batteriet ersätts med felaktig batterityp. Batterier ska kasseras enligt de lokala miljövårdsbestämmelserna.

(Swedish)

⚠ VARO

Räjähdysvaara, jos pariston tyyppi on väärä. Paristot on kierrätettävä, jos se on mahdollista. Käytetyt paristot on hävitettävä paikallisten ympäristömääräysten mukaisesti.

(Finnish)

⚠ VORSICHT

Bei falschem Einsetzen einer neuen Batterie besteht Explosionsgefahr. Die Batterie darf nur durch denselben oder einen entsprechenden, vom Hersteller empfohlenen Batterietyp ersetzt werden. Entsorgen Sie verbrauchte Batterien den Anweisungen des Herstellers entsprechend.

(German)

⚠ AVVERTIMENTO

Esiste il pericolo di un esplosione se la pila non viene sostituita in modo corretto. Utilizzare solo pile uguali o di tipo equivalente a quelle consigliate dal produttore. Per disfarsi delle pile usate, seguire le istruzioni del produttore.

(Italian)

⚠ PRECAUCIÓN

Existe peligro de explosión si la pila no se cambia de forma adecuada. Utilice solamente pilas iguales o del mismo tipo que las recomendadas por el fabricante del equipo. Para deshacerse de las pilas usadas, siga igualmente las instrucciones del fabricante.

(Spanish)

⚠ WAARSCHUWING

Er bestaat ontploffingsgevaar als de batterij wordt vervangen door een onjuist type batterij. Batterijen moeten zoveel mogelijk worden gerecycled. Houd u bij het weggooien van gebruikte batterijen aan de plaatselijke milieuwetgeving.

(Dutch)

⚠ ATENÇÃO

Haverá risco de explosão se a bateria for substituída por um tipo de bateria incorreto. As baterias devem ser recicladas nos locais apropriados. A eliminação de baterias usadas deve ser feita de acordo com as regulamentações ambientais da região.

(Brazilian Portuguese)

To replace the battery, follow these steps:

1. Observe the precautions in "Before You Begin" (see page 21).
2. Turn off all peripheral devices connected to the computer. Disconnect the computer's power cord from the AC power source (wall outlet or power adapter).
3. Remove the computer cover.
4. Locate the battery on the board (see Figure 12).
5. With a medium flat-bladed screwdriver, gently pry the battery free from its connector. Note the orientation of the "+" and "-" on the battery.
6. Install the new battery in the connector, orienting the "+" and "-" correctly.
7. Replace the computer cover.



Figure 12. Removing the Battery

3 Updating the BIOS

This chapter tells you how to update the BIOS by either using the Intel® Express BIOS Update utility or the Intel® Flash Memory Update Utility, and how to recover the BIOS if an update fails.

Updating the BIOS with the Intel® Express BIOS Update Utility

With the Intel Express BIOS Update utility you can update the system BIOS while in the Windows environment. The BIOS file is included in an automated update utility which combines the functionality of the Intel Flash Memory Update Utility and the ease-of use of Windows-based installation wizards.

To update the BIOS with the Intel Express BIOS Update utility:

1. Go to the Intel World Wide Web site:
   http://support.intel.com/support/motherboards/desktop/
2. Navigate to the Desktop Board D845GRG or D845GBV page and click the Express BIOS Update utility file for the Desktop Board D845GRG or D845GBV BIOS.
3. Download the file to your hard drive. (You can also save this file to a diskette. This is useful if you are updating the BIOS for multiple identical systems.)
4. Close all other applications. This step is required. Your system will be rebooted at the last Express BIOS Update window.
5. Double-click the executable file from the location on your hard drive where it was saved. This runs the update program.
6. Follow the instructions provided in the dialog boxes to complete the BIOS update.

Updating the BIOS with the Intel® Flash Memory Update Utility

With the Intel Flash Memory Update Utility you can update the system BIOS from a floppy disk or other bootable media. The utility available from the Web provides a simple method for creating a bootable flash memory update floppy that will automatically update your BIOS.

Obtaining the BIOS Update File

You can update to a new version of the BIOS by using the BIOS update file. The BIOS update file is a compressed self-extracting archive that contains all the files you need to update the BIOS. The BIOS update file contains:

- New BIOS files
- BIOS recovery files
- Intel Flash Memory Update Utility

You can obtain the BIOS update file through your computer supplier or by navigating to the Desktop Board D845GRG or D845GBV page on the Intel World Wide Web site:

http://support.intel.com/support/motherboards/desktop

✎ NOTE

Please review the instructions distributed with the update utility before attempting a BIOS update.

The Intel Flash Memory Update Utility allows you to:

- Update the BIOS in flash memory
- Update the language section of the BIOS

Updating the BIOS

⚠ CAUTION

The AUTOEXEC.BAT file provided with the update files updates the BIOS. Do not interrupt the process or the system may not function.

1. Boot the computer with the BIOS update diskette in drive A. During system boot, the AUTOEXEC.BAT file provided with the update files will automatically run the BIOS update process.
2. When the update process is complete, the monitor will display a message telling you to remove the diskette and to reboot the system.
3. As the computer boots, check the BIOS identifier (version number) to make sure the update was successful. If a logo appears, press <Esc> to view the POST messages.

Recovering the BIOS

It is unlikely that anything will interrupt the BIOS update; however, if an interruption occurs, the BIOS could be damaged. The following steps explain how to recover the BIOS if an update fails. The following procedure uses recovery mode for the Setup program. See page 30 for more information on Setup modes.

NOTE

Because of the small amount of code available in the boot block area, there is no video support. You will not see anything on the screen during this procedure. Monitor the procedure by listening to the speaker and looking at the diskette drive LED.

1. Turn off the computer, disconnect the computer's power cord, and disconnect all external peripherals.
2. Remove the computer cover and locate the configuration jumper block (J9G1) (see Figure 11).
3. Remove the jumper from all pins as shown below to set recovery mode for Setup.

4. Insert the bootable BIOS update diskette into diskette drive A.
5. Replace the computer cover, connect the power cord, turn on the computer, and allow it to boot. The recovery process will take a few minutes.
6. Listen to the speaker:
   - Upon applying power, drive A will begin to show activity. In about a minute, two beeps are heard and drive A activity ceases (temporarily) indicating the successful recovery of the BIOS core. Drive A activity will begin again followed by two more beeps indicating the successful recovery of the boot block. This sequence of events indicates a successful BIOS recovery.
   - A series of continuous beeps indicates a failed BIOS recovery.
7. If recovery fails, return to step 1 and repeat the recovery process.
8. If recovery is successful, turn off the computer, and disconnect its power cord.
9. Remove the computer cover and continue with the following steps.
10. On the jumper block (J9G1), reinstall the jumper back on pins 1-2 as shown below to set normal mode for Setup.

11. Leave the update diskette in drive A, replace the computer cover, and connect the computer's power cord.
12. Turn on the computer and continue with the BIOS update.

4 Using the BIOS Setup Program

The BIOS Setup program can be used to view and change the BIOS settings for the computer. The BIOS Setup program is accessed by pressing the <F2> key after the Power-On Self-Test (POST) memory test begins and before the operating system boot begins.

NOTE

The BIOS Setup menus described in this section may not show the latest settings. For the latest BIOS settings, refer to the Intel Desktop Board D845GRG/D845GBV Technical Product Specification *or the Intel World Wide Web site:*

http://support.intel.com/support/motherboards/desktop

NOTE

For reference purposes, you should write down the current Setup settings. When you make changes to the settings, update this record.

NOTE

The Setup menus described in this section apply to the desktop boards with BIOS identifier RG84510A.86A. Boards with other BIOS identifiers might have differences in some of the Setup menu screens.

The Setup screen menu bar is shown below.

Maintenance	Main	Advanced	Security	Power	Boot	Exit

Table 5 shows the BIOS Setup program menu bar.

Table 5. BIOS Setup Program Menu Bar

Maintenance	Main	Advanced	Security	Power	Boot	Exit
Clears passwords and Boot Integrity Service (BIS)* credentials, and configures extended configuration memory settings	Allocates resources for hardware components	Configures advanced features available through the chipset	Sets passwords and security features	Configures power management features	Selects boot options and power supply controls	Saves or discards changes to set program options

* For information about the BIS, refer to the Intel Web site at:

http://developer.intel.com/design/security/index1.htm

Table 6 shows the function keys available for menu screens.

Table 6. BIOS Setup Program Function Keys

BIOS Setup Program Function Key	Description
<←> or <→>	Selects a different menu screen
<↑> or <↓>	Moves cursor up or down
<Tab>	Moves cursor to the next field
<Enter>	Executes command or selects the submenu
<F9>	Load the default configuration values for the current menu
<F10>	Save the current values and exits the BIOS Setup program
<Esc>	Exits the menu

Maintenance Menu

Maintenance	Main	Advanced	Security	Power	Boot	Exit

The menu shown in Table 7 is used to clear the Setup passwords. Setup only displays this menu in configure mode. See page 30 for information about setting configure mode.

Table 7. Maintenance Menu

Feature	Options	Description
Clear All Passwords	• Ok • Cancel	Clears both the user and supervisor passwords.
Clear BIS Credentials	• Ok • Cancel	Clears the Wired for Management Boot Integrity Service (BIS) credentials.
CPU Stepping Signature	No options	Displays processor's Stepping Signature.
CPU Microcode Update Revision	No options	Displays processor's Microcode Update Revision.

* For information about the BIS, refer to the Intel Web site at:

http://developer.intel.com/design/security/index1.htm

Main Menu

Maintenance	**Main**	Advanced	Security	Power	Boot	Exit

Table 8 describes the Main Menu. This menu reports processor and memory information and is used to configure the system date and system time.

Table 8. Main Menu

Feature	Options	Description
BIOS Version	No options	Displays the version of the BIOS.
Processor Type	No options	Displays processor type.
Processor Speed	No options	Displays processor speed.
System Bus Speed	No options	Displays the system bus speed.
System Memory Speed	No options	Dislays the system memory speed.
Cache RAM	No options	Displays the size of second-level cache and whether it is ECC-capable.
Total Memory	No options	Displays the total amount of RAM.
Memory Bank 0 Memory Bank 1	No options	Displays the amount and type of RAM in the memory banks.
Language	• **English (default)** • Espanol	Selects the current default language used by the BIOS.
System Time	Hour, minute, and second	Specifies the current time.
System Date	Day of week Month/day/year	Specifies the current date.

Advanced Menu

Maintenance	Main	**Advanced**	Security	Power	Boot	Exit

PCI Configuration
Boot Configuration
Peripheral Configuration
IDE Configuration
Diskette Configuration
Event Log Configuration
Video Configuration
USB Configuration
Chipset Configuration

Table 9 describes the Advanced Menu. This menu is used to set advanced features that are available through the chipset.

Table 9. Advanced Menu

Feature	Options	Description
PCI Configuration	No options	Configures individual PCI slot's IRQ priority. When selected, displays the PCI Configuration submenu.
Boot Configuration	No options	Configures Plug & Play and the Numlock key, and resets configuration data. When selected, displays the Boot Configuration submenu.
Peripheral Configuration	No options	Configures peripheral ports and devices. When selected, displays the Peripheral Configuration submenu.
IDE Configuration	No options	Specifies type of connected IDE device.
Diskette Configuration	No options	Configures the floppy drive(s). When selected, displays the Diskette Configuration submenu.
Event Log Configuration	No options	Configures event logging. When selected, displays the Event Log Configuration submenu.
Video Configuration	No options	Configures video features. When selected, displays the Video Configuration submenu.
USB Configuration	No options	Configures USB features. When selected, displays the USB Configuration submenu.
Chipset Configuration	No options	Configures chipset features. When selected, displays the Chipset Configuration submenu.

PCI Configuration Submenu

Maintenance	Main	**Advanced**	Security	Power	Boot	Exit

PCI Configuration
Boot Configuration
Peripheral Configuration
IDE Configuration
Diskette Configuration
Event Log Configuration
Video Configuration
USB Configuration
Chipset Configuration

The submenu shown in Table 10 is used to configure the IRQ priority of PCI slots individually.

Table 10. PCI Configuration Submenu

Feature	Options	Description
• PCI Slot 1 IRQ Priority	• **Auto (default)** • 3 • 5 • 9 • 10 • 11	Allows selection of IRQ priority.
• PCI Slot 2 IRQ Priority	• **Auto (default)** • 3 • 5 • 9 • 10 • 11	Allows selection of IRQ priority and S5 wake.
• PCI Slot 3 IRQ Priority	• **Auto (default)** • 3 • 5 • 9 • 10 • 11	Allows selection of IRQ priority.
• PCI Slot 4 IRQ Priority (Note)	• **Auto (default)** • 3 • 5 • 9 • 10 • 11	Allows selection of IRQ priority.
• PCI Slot 5 IRQ Priority (Note)	• **Auto (default)** • 3 • 5 • 9 • 10 • 11	Allows selection of IRQ priority.
• PCI Slot 6 IRQ Priority (Note)	• **Auto (default)** • 3 • 5 • 9 • 10 • 11	Always set to Auto.

Note: PCI slots 4, 5, and 6 are available only on Desktop Board D845GBV.

Boot Configuration Submenu

Maintenance	Main	**Advanced**	Security	Power	Boot	Exit

PCI Configuration
Boot Configuration
Peripheral Configuration
IDE Configuration
Diskette Configuration
Event Log Configuration
Video Configuration
USB Configuration
Chipset Configuration

The submenu shown in Table 11 is used to set the Plug & Play options and the power-on state of the Numlock key.

Table 11. Boot Configuration Submenu

Feature	Options	Description
Plug & Play O/S	• **No (default)** • Yes	Specifies if manual configuration is desired. *No* lets the BIOS configure all devices in the system. This setting is appropriate when using a Plug and Play operating system. *Yes* lets the operating system configure Plug & Play (PnP) devices not required for boot if your system has a Plug & Play operating system. This option is available for use during lab testing.
Numlock	• Off • **On (default)**	Specifies the power-on state of the Numlock feature on the numeric keypad of the keyboard.

Peripheral Configuration Submenu

Maintenance	Main	**Advanced**	Security	Power	Boot	Exit

PCI Configuration
Boot Configuration
Peripheral Configuration
IDE Configuration
Diskette Configuration
Event Log Configuration
Video Configuration
USB Configuration
Chipset Configuration

This submenu shown in Table 12 is used for configuring computer peripherals.

Table 12. Peripheral Configuration Submenu

Feature	Options	Description
Serial Port A	• Disabled • Enabled • **Auto (default)**	Configures serial port A. *Auto* assigns the first free COM port, normally COM1, the address 3F8h, and the interrupt IRQ4. An * (asterisk) displayed next to an address indicates a conflict with another device.
Base I/O Address (This feature is present only when Serial Port A is set to *Enabled*)	• **3F8 (default)** • 2F8 • 3E8 • 2E8	Specifies the base I/O address for serial port A, if serial port A is Enabled.
Interrupt (This feature is present only when Serial Port A is set to *Enabled*)	• IRQ 3 • **IRQ 4 (default)**	Specifies the interrupt for serial port A, if serial port A is Enabled.
Parallel Port	• Disabled • Enabled • **Auto (default)**	Configures the parallel port. *Auto* assigns LPT1 the address 378h and the interrupt IRQ7. An * (asterisk) displayed next to an address indicates a conflict with another device.
Mode	• Output only • **Bi-directional (default)** • EPP • ECP	Selects the mode for the parallel port. Not available if the parallel port is disabled. *Output Only* operates in AT†-compatible mode. *Bi-directional* operates in PS/2†-compatible mode. *EPP* is Extended Parallel Port mode, a high-speed bi-directional mode. *ECP* is Enhanced Capabilities Port mode, a high-speed bi-directional mode.

continued

Table 12. Peripheral Configuration Submenu (continued)

Feature	Options	Description
Base I/O Address (This feature is present only when Parallel Port is set to *Enabled*)	• **378 (default)** • 278	Specifies the base I/O address for the parallel port, if Parallel Port is Enabled.
Interrupt (This feature is present only when Parallel Port is set to *Enabled*)	• IRQ 5 • **IRQ 7 (default)**	Specifies the interrupt for the parallel port, if Parallel Port is Enabled.
Audio	• Disabled • **Enabled (default)**	Enables or disables the onboard audio subsystem.
LAN Device (This feature is present only when there is onboard LAN)	• Disabled • **Enabled (default)**	Enables or disables the LAN device.

IDE Configuration Submenu

Maintenance	Main	**Advanced**	Security	Power	Boot	Exit

PCI Configuration
Boot Configuration
Peripheral Configuration
IDE Configuration
Diskette Configuration
Event Log Configuration
Video Configuration
USB Configuration
Chipset Configuration

This submenu shown in Table 13 is used to configure IDE device options.

Table 13. IDE Configuration Submenu

Feature	Options	Description
IDE Controller	• Disabled • Primary • Secondary • **Both (default)**	Specifies the integrated IDE controller. *Disabled* disables the integrated IDE controller. *Primary* enables only the primary IDE controller. *Secondary* enables only the secondary IDE controller. *Both* enables both IDE controllers.
PCI IDE Bus Master	• Disabled • **Enabled (default)**	Allows for a PCI device to initiate a transaction as a master.
Hard Disk Pre-Delay	• **Disabled (default)** • 3 Seconds • 6 Seconds • 9 Seconds • 12 Seconds • 15 Seconds • 21 Seconds • 30 Seconds	Specifies the hard disk drive pre-delay. Causes the BIOS to insert a delay before attempting to detect IDE drives in the system.
Primary IDE Master	No options	Reports type of connected IDE device. When selected, displays the Primary IDE Master submenu.
Primary IDE Slave	No options	Reports type of connected IDE device. When selected, displays the Primary IDE Slave submenu.
Secondary IDE Master	No options	Reports type of connected IDE device. When selected, displays the Secondary IDE Master submenu.
Secondary IDE Slave	No options	Reports type of connected IDE device. When selected, displays the Secondary IDE Slave submenu.

Primary/Secondary IDE Master/Slave Submenus

Maintenance	Main	**Advanced**	Security	Power	Boot	Exit

PCI Configuration	
Boot Configuration	
Peripheral Configuration	
IDE Configuration	➜ **Primary IDE Master**
Diskette Configuration	**Primary IDE Slave**
Event Log Configuration	**Secondary IDE Master**
Video Configuration	**Secondary IDE Slave**
USB Configuration	
Chipset Configuration	

There are four IDE submenus: Primary master, primary slave, secondary master, and secondary slave. Table 14 shows the format of these IDE submenus. For brevity, only one example is shown.

Table 14. Primary/Secondary IDE Master/Slave Submenus

Feature	Options	Description
Drive Installed	None	Displays the type of drive installed.
Type	• **Auto (default)** • User	Specifies the IDE configuration mode for IDE devices. *Auto* fills-in capabilities from ATA/ATAPI device. *User* allows capabilities to be changed.
Maximum Capacity	None	Displays the capacity of the drive.
LBA Mode Control (Note)	None	Specifies LBA mode control.
Block Mode	• Disabled • 2 Sectors • 4 Sectors • 8 Sectors • **16 Sectors (default)**	Specifies number of sectors per block for transfers from the hard disk drive to memory. Check the hard disk drive's specifications for optimum setting.
PIO Mode (Note)	• **Auto (default)** • 0 • 1 • 2 • 3 • 4	Specifies the PIO mode.
Ultra DMA	• **Disabled (default)** • Mode 0 • Mode 1 • Mode 2 • Mode 3 • Mode 4 • Mode 5	Specifies the Ultra DMA mode for the drive.
Cable Detected (Note)	None	Displays the type of cable connected to the IDE interface: 40-conductor or 80-conductor (for ATA-66/100 devices).

Note: These configuration options appear only if an IDE device is installed.

Diskette Configuration Submenu

Maintenance	Main	**Advanced**	Security	Power	Boot	Exit

PCI Configuration
Boot Configuration
Peripheral Configuration
IDE Configuration
Diskette Configuration
Event Log Configuration
Video Configuration
USB Configuration
Chipset Configuration

This submenu shown in Table 15 is used to configure the floppy drive.

Table 15. Diskette Configuration Submenu

Feature	Options	Description
Floppy Controller	• Disabled • **Enabled (default)**	Configures the integrated floppy controller.
Floppy A	• Disabled • 360 KB 5¼” • 1.2 MB 5¼” • 720 KB 3½” • **1.44 MB 3½” (default)** • 2.88 MB 3½”	Selects the floppy drive type.
Floppy Write Protect	• **Disabled (default)** • Enabled	Disables or enables diskette drive write protection.

Event Log Configuration Submenu

Maintenance	Main	**Advanced**	Security	Power	Boot	Exit

PCI Configuration
Boot Configuration
Peripheral Configuration
IDE Configuration
Diskette Configuration
Event Log Configuration
Video Configuration
USB Configuration
Chipset Configuration

The submenu shown in Table 16 is used to configure the event logging features.

Table 16. Event Log Configuration Submenu

Feature	Options	Description
Event Log	No options	Indicates if there is space available in the event log.
View Event Log	[Enter]	Views the contents of the DMI event log.
Clear Event Log	No options	Discards all events in the event log.
Event Logging	• Disabled • **Enabled (default)**	*Enabled* allows logging of DMI events.
Mark Events As Read	[Enter]	Marks all DMI events in the event log as read.

Video Configuration Submenu

Maintenance	Main	**Advanced**	Security	Power	Boot	Exit

PCI Configuration
Boot Configuration
Peripheral Configuration
IDE Configuration
Diskette Configuration
Event Log Configuration
Video Configuration
USB Configuration
Chipset Configuration

The submenu shown in Table 17 is used to configure video features.

Table 17. Video Configuration Submenu

Feature	Options	Description
Graphics Aperture Size	• 4MB • 8MB • 16MB • 32MB • **64MB (default)** • 128MB • 256MB	Amount of system memory available for direct access by the graphics device.
Primary Video Adapter	• **AGP (default)** • PCI	Allows selecting and AGP or PCI video controller as the display device that will be active when the system boots.
Frame Buffer Size	• 512 KB • **1 MB (default)** • 8 MB	Controls how much system RAM is reserved for use by the internal graphics device.

USB Configuration Submenu

Maintenance	Main	**Advanced**	Security	Power	Boot	Exit

PCI Configuration
Boot Configuration
Peripheral Configuration
IDE Configuration
Diskette Configuration
Event Log Configuration
Video Configuration
USB Configuration
Chipset Configuration

The menu shown in Table 18 is used to configure USB features.

Table 18. USB Configuration Submenu

Feature	Options	Description
High Speed USB	• Disabled • **Enabled (default)**	Disable this option when a USB 2.0 driver is not available.
Legacy USB Support	• Disabled • **Enabled (default)**	Enables support for legacy USB.

Chipset Configuration Submenu

Maintenance	Main	**Advanced**	Security	Power	Boot	Exit

PCI Configuration
Boot Configuration
Peripheral Configuration
IDE Configuration
Diskette Configuration
Event Log Configuration
Video Configuration
USB Configuration
Chipset Configuration

The menu shown in Table 19 is used to configure advanced chipset features.

Table 19. Chipset Configuration Submenu

Feature	Options	Description
Extended Configuration	• **Default (default)** • User Defined	Chooses the default or user defined settings for the extended configuration options.
SDRAM Frequency	• **Auto (default)** • 200 MHz • 266 MHz	Allows override of detected memory frequency value.
SDRAM Timing Control	• **Auto (default)** • Manual – Aggressive • Manual – User Defined	*Auto* allows timings to be programmed according to the memory detected. *Manual – Aggressive* selects the most aggressive user defiend timings. *Manual – User Defined* allows manual override of detected SDRAM settings
SDRAM RAS Act. To Pre.	• 7 • 6 • 5 • **Auto (default)**	Selects length of time from read to pre-change.
SDRAM CAS# Latency	• 3 • 2 • **Auto (default)**	Selects the number of clock cycles required to address a column in memory.
SDRAM RAS# to CAS# delay	• 3 • 2 • **Auto (default)**	Selects the number of clock cycles between addressing a row and addressing a column.
SDRAM RAS# Precharge	• 3 • 2 • **Auto (default)**	Selects the length of time required before accessing a new row.

Security Menu

Maintenance	Main	Advanced	**Security**	Power	Boot	Exit

The menu shown in Table 20 is used to set passwords and security features.

Table 20. Security Menu

If no password entered previously:		
Feature	**Options**	**Description**
Supervisor Password Is	No options	Reports if there is a supervisor password set.
User Password Is	No options	Reports if there is a user password set.
Set Supervisor Password	Password can be up to seven alphanumeric characters.	Specifies the supervisor password.
Set User Password	Password can be up to seven alphanumeric characters.	Specifies the user password.
Clear User Password (Note 1)	• **Yes (default)** • No	Clears the user password.
User access Level (Note 2)	• Limited • No access • View Only • **Full (default)**	Sets BIOS Setup Utility access rights for user level.

Notes:

1. This feature appears only if a user password has been set.
2. This feature appears only if both a user password and a supervisor password have been set.

Power Menu

Maintenance	Main	Advanced	Security	**Power**	Boot	Exit

The menu shown in Table 21 is used to set power management features.

Table 21. Power Menu

Feature	Options	Description
ACPI	No Options	When selected, displays the ACPI submenu.
After Power Failure	• Stay Off • **Last State (default)** • Power On	Determines the mode of operation if a power loss occurs. *Stay Off* keeps the power off until the power button is pressed. *Last State* restores the previous power state before power loss occurred. *Power On* restores power to the computer.
Wake on PCI PME	• **Stay Off (default)** • Power-On	Determines how the system responds to a PCI-PME wake up event.
Wake on Modem Ring	• **Stay Off (default)** • Power-On	Specifies how the computer responds to a Modem Ring wake up event on an installed modem.

ACPI Submenu

Maintenance	Main	Advanced	Security	**Power**	Boot	Exit
				ACPI		

The submenu represented in Table 22 is for setting the ACPI features.

Table 22. ACPI Submenu

Feature	Options	Description
Suspend Mode	• **S1 (POS) only (default)** • S1 & S3 (STR)	Specifies the ACPI sleep state.
Wake on LAN from S5	• **Stay Off (default)** • Power On	In ACPI soft-off mode only, determines how the system responds to a LAN wake up event when the system is in the ACPI soft-off mode.

Boot Menu

Maintenance	Main	Advanced	Security	Power	**Boot**	Exit

The menu shown in Table 23 is used to set the boot features and the boot sequence.

Table 23. Boot Menu

Feature	Options	Description
Silent Boot	• Disabled • **Enabled (default)**	*Disabled* displays normal POST messages. *Enabled* displays OEM logo instead of POST messages.
Intel® Rapid BIOS Boot	• Disabled • **Enabled (default)**	Allows BIOS to skip certain tests while booting.
Scan User Flash Area	• Disabled • **Enabled (default)**	Enables the BIOS to scan the flash ROM for user binary files that are executed at boot time.
PXE Boot to LAN	• **Disabled (default)** • Enabled	Disables or enables PXE boot to LAN.
USB Boot	• Disabled • **Enabled (default)**	Disables or enables booting to USB boot devices.
Boot Device Priority	No options	Specifies the boot sequence from the available types of boot devices.
Hard Disk Drives	No options	Specifies the boot sequence from the available hard disk drives.
Removable Devices	No options	Specifies the boot sequence from the available removable devices.
ATAPI CD-ROM Drives	No options	Specifies the boot sequence from the available ATAPI CD-ROM drives.

Boot Device Priority Submenu

Maintenance	Main	Advanced	Security	Power	**Boot**	Exit
					Boot Device Priority	
					Hard Disk Drives	
					Removable Devices	
					ATAPI CD-ROM Drives	

The submenu represented in Table 24 is for setting boot devices priority.

Table 24. Boot Device Priority Submenu

Feature	Options	Description
1st Boot Device 2nd Boot Device 3rd Boot Device	• Removable Device • Hard Drive • ATAPI CD-ROM • Disabled	Specifies the boot sequence from the available devices. To specify boot sequence: 1. Select the boot device with <↑> or <↓>. 2. Press <Enter> to set the selection as the intended boot device. The operating system assigns a drive letter to each boot device in the order listed. Changing the order of the devices changes the drive lettering. The default settings for the first through final boot devices are, respectively listed below. The BIOS supports up to sixteen total boot devices in any combination of the boot device types below, with respect to these maximums per type. • Removable Device (maximum of four). • Hard Drive (maximum of 12). • ATAPI CD-ROM (maximum of four).

Hard Disk Drives Submenu

Maintenance	Main	Advanced	Security	Power	**Boot**	Exit
					Boot Device Priority	
					Hard Disk Drives	
					Removable Devices	
					ATAPI CD-ROM Drives	

The submenu shown in Table 25 is for setting hard disk drives.

Table 25. Hard Disk Drives Submenu

Feature	Options	Description
1st Hard Disk Drive (Note)	Dependent on installed hard drives	Specifies the boot sequence from the available hard disk drives. To specify boot sequence: 1. Select the boot device with <↑> or <↓>. 2. Press <Enter> to set the selection as the intended boot device.

Note: This boot device submenu appears only if at least one boot device of this type is installed. This list will display up to twelve hard disk drives, the maximum number of hard disk drives supported by the BIOS.

Removable Devices Submenu

Maintenance	Main	Advanced	Security	Power	**Boot**	Exit
					Boot Device Priority	
					Hard Disk Drives	
					Removable Devices	
					ATAPI CD-ROM Drives	

The submenu in shown Table 26 is for setting removable devices.

Table 26. Removable Devices Submenu

Feature	Options	Description
1st Removable Device (Note)	Dependent on installed removable devices	Specifies the boot sequence from the available removable devices. To specify boot sequence: 1. Select the boot device with <↑> or <↓>. 2. Press <Enter> to set the selection as the intended boot device.

Note: This boot device submenu appears only if at least one boot device of this type is installed. This list will display up to four removable devices, the maximum number of removable devices supported by the BIOS.

ATAPI CD-ROM Drives

Maintenance	Main	Advanced	Security	Power	**Boot**	Exit
					Boot Device Priority	
					Hard Disk Drives	
					Removable Devices	
					ATAPI CD-ROM Drives	

The submenu shown in Table 27 is for setting ATAPI CD-ROM drives.

Table 27. ATAPI CD-ROM Drives Submenu

Feature	Options	Description
1st ATAPI CD-ROM Drive (Note)	Dependent on installed ATAPI CD-ROM drives	Specifies the boot sequence from the available ATAPI CD-ROM drives. To specify boot sequence: 1. Select the boot device with <↑> or <↓>. 2. Press <Enter> to set the selection as the intended boot device.

Note: This boot device submenu appears only if at least one boot device of this type is installed. This list will display up to four ATAPI CD-ROM drives, the maximum number of ATAPI CD-ROM drives supported by the BIOS.

Exit Menu

Maintenance	Main	Advanced	Security	Power	Boot	**Exit**

The menu shown in Table 28 is used to exit the BIOS Setup program, saving changes, and loading and saving defaults.

Table 28. Exit Menu

Feature	Description
Exit Saving Changes	Exits and saves the changes in CMOS SRAM.
Exit Discarding Changes	Exits without saving any changes made in the BIOS Setup program.
Load Optimal Defaults	Loads optimal defaults.
Load Custom Defaults	Loads the custom defaults for Setup options.
Save Custom Defaults	Saves the current values as custom defaults. Normally, the BIOS reads the Setup values from flash memory. If this memory is corrupted, the BIOS reads the custom defaults. If no custom defaults are set, the BIOS reads the factory defaults.
Discard Changes	Discards changes without exiting Setup. The option values present when the computer was turned on are used.

5 Technical Reference

Board Connectors

Intel desktop board connectors can be divided into three groups:

- Back panel connectors
- Midboard connectors
  - Audio connectors
  - Power and hardware connectors
  - Add-in board and peripheral interface connectors
- Front panel headers

⚠ CAUTION

Many of the midboard and front panel connectors provide operating voltage (+5 V dc and +12 V dc, for example) to devices inside the computer chassis, such as fans and internal peripherals. These connectors are not overcurrent protected. Do not use these connectors for powering devices external to the computer chassis. A fault in the load presented by the external devices could cause damage to the computer, the interconnecting cable, and the external devices themselves.

Back Panel Connectors

Figure 13 shows the back panel connectors.



Item	Description	Color
A	PS/2 mouse port	Green
B	PS/2 keyboard port	Purple
C	USB 2.0 port 0	Black
D	USB 2.0 port 1	Black
E	Parallel port	Burgundy
F	Serial port A	Teal
G	VGA port	Blue
H	RJ-45 (optional)	Black
I	USB 2.0 port 2	Black
J	USB 2.0 port 3	Black
K	Mic in	Pink
L	Audio line out	Lime green
M	Audio line in	Light blue

Figure 13. Back Panel Connectors

NOTE

The line out connector, located on the back panel, is designed to power either headphones or amplified speakers only. Poor audio quality may occur if passive (non-amplified) speakers are connected to this output.

Midboard Connectors

Audio Connectors

Figure 14 shows the location of the audio connectors.



Item	Description	Color
A	Front panel audio	Black
B	Auxiliary line in (ATAPI)	White
C	CD-ROM (ATAPI)	Black

Figure 14. Audio Connectors

Table 29 shows the pin assignments for the front panel audio header.

Table 29. Front Panel Audio Header Signal Names (J8A1)

Pin	Signal Name	Pin	Signal Name
1	AUD-MIC	2	AUD-GND
3	AUD-MIC-BIAS	4	AUD-VCC
5	AUD-FPOUT-R	6	AUD-RET-R
7	HP-ON	8	KEY
9	AUD-FPOUT-L	10	AUD-RET-L

Power and Hardware Connectors

CAUTION

Failure to use an ATX12V power supply, or not connecting the additional power supply lead to the Desktop Boards D845GRG or D845GBV may result in damage to the desktop board.

Desktop Boards D845GRG and D845GBV require an ATX12V compliant power supply to function according to desktop board specifications. Both boards have two ATX12V compliant power supply connectors that are needed to provide extra power to the Intel 845G chipset and Pentium 4 processor.

Figure 15 shows the power and hardware connectors.



Item	Description	Item	Description
A	Rear chassis fan (tachometer input)	E	SCSI hard drive activity LED
B	ATX12V power	F	Chassis intrusion
C	Processor fan (tachometer input)	G	Front chassis fan
D	Main power		

Figure 15. Power and Hardware Control Connectors

Add-In Card and Peripheral Interface Connectors

Figure 16 shows the add-in card and peripheral interface connectors for Desktop Board D845GBV. Desktop Board D845GRG has three PCI slots.



Item	Description	Item	Description
A	CNR (optional)	G	PCI bus connector 1
B	PCI bus connector 6	H	AGP
C	PCI bus connector 5	I	Floppy drive
D	PCI bus connector 4	J	Primary IDE
E	PCI bus connector 3	K	Secondary IDE
F	PCI bus connector 2 (SMBus routed)		

Figure 16. Desktop Board D845GBV Add-in Card and Peripheral Interface Connectors

Front Panel Headers

Figure 17 shows the location of the front panel headers.



Item	Description
A	Front panel audio (see Table 29 on page 65 for pin assignments)
B	Front panel USB
C	Front panel
D	Alternate power/sleep LED

Figure 17. Front Panel Headers

Table 30 shows the pin assignments for the front panel USB 2.0 header.

Table 30. Front Panel USB 2.0 Header (J9F1)

Pin	Signal name	Pin	Signal name
1	VREG_FP_WSBPWR0	2	VREG_FP_USBPWR0
3	USB_FPP0-	4	USB_FPP1-
5	USB_FPP0+	6	USB_FPP1+
7	Ground	8	Ground
9	Key	10	USB_FP_OC0

Note: USB ports may be assigned as needed.

Table 31 shows the pin assignments for the front panel header.

Table 31. Front Panel Header (J9G1)

Pin	Signal	In/Out	Description	Pin	Signal	In/Out	Description
Hard Drive Activity LED				**Power LED**			
1	HD_PWR	Out	Hard disk LED pull-up (330 Ω) to +5 V	2	HDR_BLNK_GRN	Out	Front panel green LED
3	HDA#	Out	Hard disk active LED	4	HDR_BLNK_YEL	Out	Front panel yellow LED
Reset Switch				**On/Off Switch**			
5	Ground		Ground	6	SWITCH_ON#	In	Power switch
7	FP_RESET#	In	Reset switch	8	Ground		Ground
9	+5 V	Out	Power	10	N/C		Not connected

Desktop Board Resources

Memory Map

Table 32. System Memory Map

Address Range (decimal)	Address Range (hex)	Size	Description
1024 K - 2097152 K	100000 - 7FFFFFF	2047 MB	Extended Memory
960 K - 1024 K	F0000 - FFFFF	64 KB	Runtime BIOS
896 K - 960 K	E0000 - EFFFF	64 KB	Reserved
800 K - 896 K	C8000 - DFFFF	96 KB	Available high DOS memory (open to the PCI bus)
640 K - 800 K	A0000 - C7FFF	160 KB	Video memory and BIOS
639 K - 640 K	9FC00 - 9FFFF	1 KB	Extended BIOS data (movable by memory manager software)
512 K - 639 K	80000 - 9FBFF	127 KB	Extended conventional memory
0 K - 512 K	00000 - 7FFFF	512 KB	Conventional memory

DMA Channels

Table 33. DMA Channels

DMA Channel Number	Data Width	System Resource
0	8 or 16 bits	
1	8 or 16 bits	Parallel port
2	8 or 16 bits	Floppy drive
3	8 or 16 bits	Parallel port (for ECP or EPP)
4	8 or 16 bits	DMA controller
5	16 bits	Open
6	16 bits	Open
7	16 bits	Open

Interrupts

Table 34. Interrupts

IRQ	System Resource
NMI	I/O channel check
0	Reserved, interval timer
1	Reserved, keyboard buffer full
2	Reserved, cascade interrupt from slave PIC
3	COM2*
4	COM1*
5	LPT2 (Plug and Play option) / **
6	Floppy drive controller
7	LPT1*
8	Real time clock
9	**
10	**
11	**
12	Onboard mouse port (if present, else user available)
13	Reserved, math coprocessor
14	Primary IDE (if present, else user available)
15	Secondary IDE (if present, else user available)

* Default, but can be changed to another IRQ.

** Dynamically allocated for all PCI/AGP devices and slots.

A Error Messages and Indicators

Desktop Boards D845GRG and D845GBV report POST errors in two ways:

- By sounding a beep code
- By displaying an error message on the monitor

BIOS Beep Codes

The BIOS beep codes are listed in Table 35. The BIOS also issues a beep code (one long tone followed by two short tones) during POST if the video configuration fails (a faulty video card or no card installed) or if an external ROM module does not properly checksum to zero.

Table 35. Beep Codes

Number of Beeps	Description
1	Refresh failure
2	Parity cannot be reset
3	First 64 K memory failure
4	Timer not operational
5	Processor failure (Reserved; not used)
6	8042 GateA20 cannot be toggled (memory failure or not present)
7	Exception interrupt error
8	Display memory R/W error
9	(Reserved; not used)
10	CMOS Shutdown register test error
11	Invalid BIOS (such as, POST module not found)

BIOS Error Messages

When a recoverable error occurs during the POST, the BIOS displays an error message describing the problem.

Table 36. BIOS Error Messages

Error Message	Explanation
GA20 Error	An error occurred with Gate-A20 when switching to protected mode during the memory test.
Pri Master HDD Error Pri Slave HDD Error Sec Master HDD Error Sec Slave HDD Error	Could not read sector from corresponding drive.
Pri Master Drive - ATAPI Incompatible Pri Slave Drive - ATAPI Incompatible Sec Master Drive - ATAPI Incompatible Sec Slave Drive - ATAPI Incompatible	Corresponding drive is not an ATAPI device. Run Setup to make sure device is selected correctly.
A: Drive Error B: Drive Error	No response from the diskette drive.
CMOS Battery Low	The battery may be losing power. Replace the battery soon.
CMOS Display Type Wrong	The display type is different than what has been stored in CMOS. Check Setup to make sure type is correct.
CMOS Checksum Bad	The CMOS checksum is incorrect. CMOS memory may have been corrupted. Run Setup to reset values.
CMOS Settings Wrong	CMOS values are not the same as the last boot. These values have either been corrupted or the battery has failed.
CMOS Date/Time Not Set	The time and/or date values stored in CMOS are invalid. Run Setup to set correct values.
DMA Error	Error during read/write test of DMA controller.
FDC Failure	Error occurred trying to access diskette drive controller.
HDC Failure	Error occurred trying to access hard disk controller.
Checking NVRAM.....	NVRAM is being checked to see if it is valid.
Update OK!	NVRAM was invalid and has been updated.
Updated Failed	NVRAM was invalid but was unable to be updated.
Keyboard Is Locked	The system keyboard lock is engaged. The system must be unlocked to continue to boot.
Keyboard Error	Error in the keyboard connection. Make sure keyboard is connected properly.
KB/Interface Error	Keyboard interface test failed.

continued

Table 36. BIOS Error Messages (continued)

Error Message	Explanation
Memory Size Decreased	Memory size has decreased since the last boot. If no memory was removed, then memory may be bad.
Memory Size Increased	Memory size has increased since the last boot. If no memory was added, there may be a problem with the system.
Memory Size Changed	Memory size has changed since the last boot. If no memory was added or removed, then memory may be bad.
No Boot Device Available	System did not find a device to boot.
Off Board Parity Error	A parity error occurred on an offboard card. This error is followed by an address.
On Board Parity Error	A parity error occurred in onboard memory. This error is followed by an address.
Parity Error	A parity error occurred in onboard memory at an unknown address.
NVRAM / CMOS / PASSWORD cleared by Jumper	NVRAM, CMOS, and passwords have been cleared. The system should be powered down and the jumper removed.
<CTRL_N> Pressed	CMOS is ignored and NVRAM is cleared. User must enter Setup.

B Regulatory Compliance

This appendix contains:

- Safety standards, electromagnetic compatibility (EMC) regulations, and product certification markings for Desktop Boards D845GRG and D845GBV.
- Instructions and precautions for integrators who are installing the desktop board in a chassis.

Safety Regulations

Desktop Boards D845GRG and D845GBV comply with the safety regulations stated in Table 37 when correctly installed in a compatible host system.

Table 37. Safety Regulations

Regulation	Title
CSA C22.2 No. 60950/ UL 60950, 3rd Edition, 2000	Bi-National Standard for Safety of Information Technology Equipment including Electrical Business Equipment. (USA and Canada)
EN 60950, 2nd Edition, 1992 (with Amendments 1, 2, 3, and 4)	The Standard for Safety of Information Technology Equipment including Electrical Business Equipment. (European Union)
IEC 60950, 2nd edition, 1991 (with Amendments 1, 2, 3, and 4)	The Standard for Safety of Information Technology Equipment including Electrical Business Equipment. (International)
EMKO-TSE (74-SEC) 207/94	Summary of Nordic deviations to EN 60950. (Norway, Sweden, Denmark, and Finland)

EMC Regulations

Desktop Boards D845GRG and D845GBV comply with the EMC regulations stated in Table 38 when correctly installed in a compatible host system.

Table 38. EMC Regulations

Regulation	Title
FCC Class B	Title 47 of the Code of Federal Regulations, Parts 2 and 15, Subpart B, Radiofrequency Devices. (USA)
ICES-003 (Class B)	Interference-Causing Equipment Standard, Digital Apparatus. (Canada)
EN55022: 1998 (Class B)	Limits and methods of measurement of Radio Interference Characteristics of Information Technology Equipment. (European Union)
EN55024: 1998	Information Technology Equipment – Immunity Characteristics Limits and methods of measurement. (European Union)
AS/NZS 3548 (Class B)	Australian Communications Authority, Standard for Electromagnetic Compatibility. (Australia and New Zealand)
CISPR 22, 3rd Edition, (Class B)	Limits and methods of measurement of Radio Disturbance Characteristics of Information Technology Equipment. (International)
CISPR 24: 1997	Information Technology Equipment – Immunity Characteristics – Limits and Methods of Measurement. (International)

Product Certification Markings

Desktop Boards D845GRG and D845GBV have the following product certification markings:

- UL joint US/Canada Recognized Component mark: consists of small c followed by a stylized backward UR and followed by a small US. Includes adjacent UL file number for Intel desktop boards: E210882 (component side).
- FCC Declaration of Conformity logo mark for Class B equipment; includes Intel name and model designation (solder side).
- CE mark: declaring compliance to European Union (EU) EMC directive (89/336/EEC) and Low Voltage directive (73/23/EEC) (component side).
- Australian Communications Authority (ACA) C-Tick mark: consists of a stylized C overlaid with a check (tick) mark (component side), followed by Intel supplier code number, N-232.
- Printed wiring board manufacturer's recognition mark: consists of a unique UL recognized manufacturer's logo, along with a flammability rating (94V-0) (solder side).
- Battery "+ Side Up" marking: located on the component side of the board in close proximity to the battery holder.
- Korean MIC logo mark: denotes Korean EMC certification (component side). Additional certification information is provided below:
  1. Product Name (model)
  2. Certificate ID
  3. Applicant: Intel Korea Ltd.
  4. Date of manufacture as separate marking on product
  5. Manufacturer (country of origin)

Korean MIC logo mark for Desktop Board D845GRG

Korean MIC logo mark for Desktop Board D845GBV

Installation Precautions

When you install and test the desktop board, observe all warnings and cautions in the installation instructions.

To avoid injury, be careful of:

- Sharp pins on connectors
- Sharp pins on printed circuit assemblies
- Rough edges and sharp corners on the chassis
- Hot components (like processors, voltage regulators, and heat sinks)
- Damage to wires that could cause a short circuit

Observe all warnings and cautions that instruct you to refer computer servicing to qualified technical personnel.

Installation Instructions

⚠ CAUTION

Follow these guidelines to meet safety and regulatory requirements when installing this board assembly.

Read and adhere to all of these instructions and the instructions supplied with the chassis and associated modules. If the instructions for the chassis are inconsistent with these instructions or the instructions for associated modules, contact the supplier's technical support to find out how you can ensure that your computer meets safety and regulatory requirements. If you do not follow these instructions and the instructions provided by chassis and module suppliers, you increase safety risk and the possibility of noncompliance with regional laws and regulations.

Ensure Electromagnetic Compatibility (EMC) Compliance

Before computer integration, make sure that the power supply and other modules or peripherals, as applicable, have passed Class B EMC testing and are marked accordingly.

In the installation instructions for the host chassis, power supply, and other modules pay close attention to the following:

- Product certifications or lack of certifications
- External I/O cable shielding and filtering
- Mounting, grounding, and bonding requirements
- Keying connectors when mating the wrong connectors could be hazardous

If the power supply and other modules or peripherals, as applicable, are not Class B EMC compliant before integration, then EMC testing is required on a representative sample of the newly completed computer.

Chassis and Component Certifications

Ensure that the chassis and certain components; such as the power supply, peripheral drives, wiring, and cables; are components certified for the country or market where used. Agency certification marks on the product are proof of certification. Typical product certifications include:

In Europe

The CE marking signifies compliance with all applicable European requirements. If the chassis and other components are not properly CE marked, a supplier's Declaration of Conformity statement to the European EMC directive and Low Voltage directive (as applicable), should be obtained. Additionally, other directives, such as the Radio and Telecommunications Terminal Equipment (R&TTE) directive may also apply depending on product features.

In the United States

A certification mark by a Nationally Recognized Testing Laboratory (NRTL) such as UL, CSA, or ETL signifies compliance with safety requirements. Wiring and cables must also be UL listed or recognized and suitable for the intended use. The FCC Class B logo for home or office use signifies compliance with electromagnetic interference (EMI) requirements.

In Canada

A nationally recognized certification mark such as CSA or cUL signifies compliance with safety requirements. The Industry Canada statement at the front of this product guide demonstrates compliance with Canadian EMC regulations. Industry Canada recognizes and accepts FCC certification as denoting compliance with national electromagnetic interference (emissions) requirements.

Prevent Power Supply Overload

Do not overload the power supply output. To avoid overloading the power supply, make sure that the calculated total current loads of all the modules within the computer is less than the output current rating of each of the power supplies output circuits.

Place Battery Marking

There is insufficient space on this desktop board to provide instructions for replacing and disposing of the Lithium ion coin cell battery. For system safety certification, the following statement or equivalent statement is required to be permanently and legibly marked on the chassis near the battery.

⚠ CAUTION

Risk of explosion if battery is incorrectly replaced.

Replace with only the same or equivalent type recommended by the manufacturer. Dispose of used batteries according to the manufacturer's instructions.

Use Only for Intended Applications

All Intel desktop processor boards are evaluated as Information Technology Equipment (I.T.E.) for use in personal computers for installation in homes, offices, schools, computer rooms, and similar locations. The suitability of this product for other applications or environments, such as medical, industrial, alarm systems, test equipment, etc. may require further evaluation.